

ALPHALAS GMBH
BERTHA-VON-SUTTNER-STR. 5
D-37085 GÖTTINGEN
GERMANY

TEL +49 - (0)551 - 77 06 147
FAX +49 - (0)551 - 77 06 146
E-MAIL INFO@ALPHALAS.COM
WEB WWW.ALPHALAS.COM



LASERS, OPTICS, ELECTRONICS. MADE IN GERMANY.

Advanced High-Speed Digital CCD Line Camera CCD-S3600-D(-UV)

**High-Sensitivity Linear CCD Array with 3648 Pixels, 16-bit ADC,
32 MB DDR2 RAM, USB 2.0, Trigger Input & Output**

**Supports Windows (WHQL Certified Driver),
Linux, Mac OS X & Other OS**

Includes Drivers & Applications for LabVIEW and C++



OPERATING MANUAL



Table of Contents

| | |
|----------------------------------------------------------------------------------------------------------------------------------------|--------|
| Table of Contents | - 2 - |
| List of Figures | - 4 - |
| Preface | - 5 - |
| 1. Getting Started | - 8 - |
| 2. The CCD-S3600-D(-UV): Introduction & Features | - 9 - |
| 2.1. Overview of the CCD Line Camera | - 9 - |
| 2.2. Fields of Application | - 10 - |
| 2.3. Ease of Use vs. Advanced Features | - 10 - |
| 2.3.1. Ease of Use for the Novice User | - 10 - |
| 2.3.2. Unique & Powerful Features for the Advanced User | - 11 - |
| 2.4. Features of the CCD Line Camera | - 11 - |
| 3. Specifications | - 16 - |
| 3.1. Detailed Specifications | - 16 - |
| 3.2. Spectral Sensitivity | - 20 - |
| 3.3. Connectors and Indicators on the Rear Panel | - 20 - |
| 3.4. Mechanical Drawing | - 21 - |
| 4. Description of Operation | - 22 - |
| 4.1. Overview of CCD Operation | - 22 - |
| 4.1.1. Collecting Light & Data Flow in the CCD-S3600-D(-UV) | - 22 - |
| 4.1.2. Sensor Pixels | - 22 - |
| 4.1.3. Exposure to Light and Integration Time | - 23 - |
| 4.1.4. Attenuation of Light | - 25 - |
| 4.1.5. Damage Threshold of the CCD Sensor | - 25 - |
| 4.1.6. Frames, Sensor Readout and Continuously Running Frame Integration - | 26 - |
| 4.1.7. Integration Time vs. Readout Time, Non-Shutter Mode vs. Shutter Mode - | 27 - |
| 4.1.8. Integration Time vs. Frame Rate | - 30 - |
| 4.1.9. Integration Time with Internal vs. External Synchronization Mode .. | - 31 - |
| 4.2. Configuration and Acquisition | - 32 - |
| 4.2.1. Configuration | - 33 - |
| 4.2.2. Acquisition and Data Modes | - 34 - |
| 4.3. CCD Operating Modes | - 36 - |
| 4.3.1. Internally Synchronized, Continuously Running with Software Capture Start - | 37 - |
| 4.3.2. Internally Synchronized, Continuously Running with Hardware Capture Start (Rising Edge Triggering) | - 38 - |
| 4.3.3. Internally Synchronized, Continuously Running with Hardware Capture ENABLE (High Level Triggering) | - 40 - |
| 4.3.4. Single Shot, Clean & Ready with External Hardware Trigger (Rising Edge Triggering), Use for $T_{int} \leq 500 \mu s$ Only | - 42 - |
| 4.3.5. Externally Synchronized, Continuously Running with Software Capture Start - | 45 - |
| 4.4. Connecting the Trigger Input Signal to the CCD | - 48 - |



| | | |
|--------|------------------------------------------------------------------------|--------|
| 4.5. | Trigger Output from the CCD | - 49 - |
| 4.5.1. | Trigger Output Indicating "Integration Start" | - 49 - |
| 4.5.2. | Trigger Output Indicating "Integration End" | - 54 - |
| 4.6. | Detailed Description of Commands and Programming | - 56 - |
| 4.6.1. | Configuration Commands | - 56 - |
| 4.6.2. | Acquisition Commands | - 60 - |
| 4.6.3. | Other Commands | - 62 - |
| 4.7. | Time Needed to Acquire, Fetch & Display Frames (Measured in LabVIEW) - | 63 - |
| 5. | Connecting the CCD & Installing the USB Drivers | - 64 - |
| 5.1. | Microsoft Windows 7 / Vista / XP | - 64 - |
| 5.2. | Linux, Mac OS X, etc. | - 65 - |
| 5.2.1. | Linux | - 65 - |
| 5.2.2. | Mac OS X | - 66 - |
| 5.2.3. | Other OS | - 66 - |
| 5.2.4. | libftdi – An Alternative to D2XX | - 66 - |
| 6. | LabVIEW Drivers & GUI Applications | - 67 - |
| 6.1. | Installing the LabVIEW Drivers | - 67 - |
| 6.1.1. | Instructions for All Operating Systems | - 67 - |
| 6.1.2. | Special Instructions for LabVIEW for Linux | - 67 - |
| 6.1.3. | Special Instructions for LabVIEW for Mac OS | - 68 - |
| 6.2. | Using the LabVIEW Drivers | - 69 - |
| 6.3. | LabVIEW Examples & GUI Application VIs | - 71 - |
| 7. | C++ Examples | - 77 - |
| 7.1. | Microsoft Visual C++ for Windows | - 77 - |
| 7.2. | GCC C++ for Linux, Mac OS X, etc. | - 78 - |
| 8. | Maintenance | - 80 - |
| 9. | Troubleshooting | - 81 - |



List of Figures

| | |
|----------------------------------------------------------------------------------------------|------|
| Figure 2-1: Simplified Block Diagram of the CCD-S3600-D(-UV) | 12 - |
| Figure 3-1: Spectral Sensitivity Chart | 20 - |
| Figure 4-1: CCD Collecting Light and CCD Data Flow | 22 - |
| Figure 4-2: Pixels on the CCD Sensor | 23 - |
| Figure 4-3: CCD Sensor Collecting Light | 23 - |
| Figure 4-4: Integration Time and Overexposure | 24 - |
| Figure 4-5: Light Attenuation | 25 - |
| Figure 4-6: Continuous Frame Integration and Readout in Parallel | 26 - |
| Figure 4-7: Frames with Integration Time \geq Readout Time : Non-Shutter Mode .. | 28 - |
| Figure 4-8: Frames with Integration Time $<$ Readout Time : Shutter Mode | 29 - |
| Figure 4-9: Initial Dummy Frame after Power Up or Reconfiguration | 32 - |
| Figure 4-10: Finishing the Acquisition and Last Readout-Only Frame | 35 - |
| Figure 4-11: Internally Synchronized, Continuously Running with Software Capture Start | 37 - |
| Figure 4-12: Internally Synchronized, Continuously Running with HW Capture Start.. | 38 - |
| Figure 4-13: Internally Synchronized, Continuously Running with HW Capture ENABLE | 40 - |
| Figure 4-14: Single Shot, Clean & Ready with External Hardware Trigger | 43 - |
| Figure 4-15: Externally Synchronized, Continuously Running with Software Capture Start | 46 - |
| Figure 4-16: A Frame in Shutter Mode with External Synchronization | 46 - |
| Figure 4-17: Trig Out at Integration Start in Non-Shutter Mode | 50 - |
| Figure 4-18: Trig Out at Integration Start in Shutter Mode (No Offset) | 51 - |
| Figure 4-19: Trig Out at Integration Start in Shutter Mode with Offset | 52 - |
| Figure 4-20: Trig Out at Integration Start used Together with Trig In | 53 - |
| Figure 4-21: Trig Out at Integration End in Ext. Synch. Mode (Non-Shutter Mode) - | 54 - |
| Figure 4-22: Trig Out at Integration End in Ext. Synch. Mode (Shutter Mode) | 55 - |
| Figure 6-1: The LabVIEW Driver in the Functions Palette | 69 - |
| Figure 6-2: The LabVIEW Driver Structure Shown in the VI Tree VI | 70 - |
| Figure 6-3: The LabVIEW Project Containing the Example VIs | 72 - |
| Figure 6-4: Acquisition Loop with Runtime Changeable Parameters VI | 73 - |
| Figure 6-5: Data Streaming to File VI | 74 - |
| Figure 6-6: View Streamed Data from File VI | 74 - |
| Figure 6-7: Acquisition Loop with 3D Graph VI | 75 - |
| Figure 6-8: Acquisition Loop with Save and Load and FWHM Calculation VI | 76 - |
| Figure 6-8: The Included Microsoft Visual C++ Project | 77 - |



Preface

Thank you very much for purchasing this product. This manual contains information for proper installation and operation. Please read it carefully as well as all additional documentation included before installing and operating the device. In order to obtain optimum performance from this product please follow the instructions. Please note that some photos may slightly differ from your specific product.

Please keep the whole documentation for your records.

ALPHALAS GmbH products are intended for expert users only. They must **not** be used where injury to persons or damage to property may occur. ALPHALAS GmbH products must **not** be used for medical or any other *in vivo* applications on human beings. They must **not** be used in critical applications (e.g. in life support systems, in aviation, in nuclear facilities, in weapon systems, in safety or security systems, etc).

Unauthorized opening of the products will void any warranty and support.

Please note that unauthorized intervention to the products, especially to the control electronics will void any warranty. If you need support please contact ALPHALAS GmbH at:

Phone: +49 - 551 - 77 06 147

Fax: +49 - 551 - 77 06 146

E-mail: support@alphalas.com

Please note that support is a service to our customers and assumes no liability for injury or damages that may result. Such support shall not affect any warranty agreements.

ALPHALAS GmbH makes every effort to provide accurate and up-to-date information in its documentation. Nevertheless, such information is subject to change without notice. ALPHALAS GmbH assumes no liability whatsoever, expressed or implied, for injury or damages resulting from any defects in its documentation.

We reserve the right to make any changes that do not deteriorate the specified performance of the product.

Please note that some parts of our products are subject to wear and tear. Therefore they have limited lifetime and are excluded from any expressed or implied warranty. The stated operation lifetime is only a statistically estimated value and may largely differ from part to part.



ALPHALAS GmbH reserves the right to make changes without further notice to any products or software herein. ALPHALAS GmbH makes no warranty, representation or guarantee regarding the suitability of its products or software for any particular purpose, nor does ALPHALAS GmbH assume any liability arising out of the application or use of any product or software, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters that may be provided in ALPHALAS GmbH data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals", must be validated for each customer application by customer's technical experts. ALPHALAS GmbH does not convey any license under its patent rights nor the rights of others. ALPHALAS GmbH products and software are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the ALPHALAS GmbH product or software could create a situation where personal injury or death may occur. Should Buyer purchase or use ALPHALAS GmbH products or software for any such unintended or unauthorized application, Buyer shall indemnify and hold ALPHALAS GmbH and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ALPHALAS GmbH was negligent regarding the design or manufacture of the part or software.

Please note: All specifications in this document are subject to change without notice. No responsibility for typing or printing errors. We reserve the right to make any changes that do not deteriorate the specified performance of our products.

Trademark notice: LabVIEW is a trademark of National Instruments Corporation. Windows is a trademark of Microsoft Corporation. Mac and Mac OS are trademarks of Apple Inc. Linux is a trademark of Linus Torvalds. All other trademarks and copyrights are the property of their respective owners.

Copyright © ALPHALAS GmbH. All rights reserved. Do not copy, share or reproduce without permission.



NOTICE REGARDING SOFTWARE INCLUDED WITH THE PRODUCT

Under the copyright laws, the software included (instrument driver, examples, etc.) may not be redistributed, reproduced or transmitted in any form, electronic or mechanical, including photocopying, recording, storing in an information retrieval system, or translating, in whole or in part, without the prior written consent of ALPHALAS GmbH. This software may be used only with the hardware it has been purchased with.

Disclaimer of Warranty

OUR SOFTWARE IS DISTRIBUTED IN THE HOPE THAT IT WILL BE USEFUL, BUT WITHOUT ANY WARRANTY. THE COPYRIGHT HOLDER PROVIDES THE SOFTWARE "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE SOFTWARE IS WITH THE CUSTOMER. SHOULD THE SOFTWARE PROVE DEFECTIVE, THE CUSTOMER ASSUMES THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

Limitation of Liability

IN NO EVENT WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MODIFIES AND/OR CONVEYS THE SOFTWARE AS PERMITTED ABOVE, BE LIABLE TO THE CUSTOMER FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE SOFTWARE (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY THE CUSTOMER OR THIRD PARTIES OR A FAILURE OF THE SOFTWARE TO OPERATE WITH ANY OTHER SOFTWARE), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. THIS LIMITATION OF THE LIABILITY WILL APPLY REGARDLESS OF THE FORM OF ACTION, WHETHER IN CONTRACT OR TORT, INCLUDING NEGLIGENCE.

For further information regarding the software included please refer to the README files included with the software.



1. Getting Started



This product is a precision instrument and must be handled with extreme care. Do not drop and do not expose to electrostatic discharges, mechanical shock or rapid temperature changes.



Carefully read the accompanying documentation before installing and operating the device. ALPHALAS GmbH is not responsible for any damages to the delivered products or any injury to persons sustained as a result of improper installation or improper usage. If you have any questions regarding installation and operation, please contact us.

1. Before unpacking the product, inspect the **packaging** for damages due to transportation. If there are any visible damages notify immediately the shipping company and ALPHALAS GmbH. Also check the status of any shock and/or tilt indicators if such indicators are attached. The shipping carrier is responsible for damage in transit.
2. **Do not open the packing box immediately if there is an outside temperature below 15°C (59°F) or if the temperature difference inside/outside is more than 5°C (9°F). In this case let the equipment thermally equalize for at least 24 hours, in order to avoid water condensation.**
3. To avoid damage, **carefully** cut and remove wrapping materials. Remove dumping foam and air bags.
4. **Inspect the equipment** immediately after opening the packaging for mechanical damages, moisture and other visible defects. Notify the shipping company and ALPHALAS GmbH immediately of potential problems.
5. **Save the original packing boxes and packing material.** They will be required if it becomes necessary to reship the equipment for service or repair.



Troubleshooting inside the device is prohibited and will void any warranty and support. The device is provided with security labels and can be opened only in ALPHALAS GmbH's production facilities. If you cannot solve a problem, please contact the customer service.



2. The CCD-S3600-D(-UV): Introduction & Features

2.1. Overview of the CCD Line Camera

The CCD-S3600-D(-UV) is a complete and easy to use high-speed digital CCD line scan camera system with many advanced features. These powerful and unique features include:

- high-sensitivity linear CCD sensor array with 3648 active pixels
- spectral range from 320 nm to 1100 nm or 200 nm to 1100 nm with UV option
- integration time programmable from 10 μ s to 1 minute in very precise 1 μ s steps
- 16-bit precise high-speed analog-to-digital converter (ADC)
- 32 MB high-speed DDR2 RAM for data storage & data buffering
- high-speed USB 2.0 interface
- state-of-the-art FPGA controller optimized for true high-speed parallel operation in hardware
- high-speed electronics
- trigger input & trigger output (with programmable offset) for synchronization from & to external devices (e.g. pulsed lasers), gold-plated SMB connectors
- maximum frame rate of 269.5 frames per second
- multiple modes of operation & precise control
- onboard data storage mode & direct data streaming mode
- capturing of an unlimited number of subsequent frames with no missing frames at the highest frame rate (only limited by the storage device used)
- many advanced features (e.g. hardware dark correction)
- very compact, lightweight and flexible hardware
- easy plug & play operation and full software control
- no need for an external power supply (powered through the USB cable)
- no need for additional components (no frame grabbers and no data acquisition boards required)
- programmable from many programming languages & software development platforms for unlimited post-processing possibilities
- multi-OS support: Windows, Linux, Mac OS, etc.
- free & ready-to-use LabVIEW drivers, fully-functional GUI applications and examples supporting LabVIEW for Windows, Linux and Mac OS X
- free USB drivers from FTDI supporting all major hardware platforms and operating systems: Windows, Linux, Mac OS X, etc.
- fully automated driver installation on operating systems like Windows 7 / Vista / XP allowing true plug & play without any need for manual driver installation, because the certified USB driver is already included in these OS
- free high-level USB interfacing libraries from FTDI for Windows (.dll), Linux (.so), Mac OS X (.dylib), etc.
- free C++ source cross-platform code demonstrating the device in use; for Microsoft Visual C++ for Windows as well as GCC for Linux, Mac OS X, etc.



- ideal for science, research, education & OEM applications
- ideal for mobile / notebook / laptop as well as desktop use

2.2. Fields of Application

Fields of application for the CCD-S3600-D(-UV) include but are not limited to various science & research areas (e.g. physics, chemistry, biology, biomedicine, medicine), lasers, optics, photonics, spectroscopy, measurements (e.g. light, fluorescence, M^2 , beam profile, single-shot autocorrelators), imaging, data acquisition, machine vision, monitoring, process control, OEM applications (e.g. industrial) and education. The device represents a cost-effective solution for the above applications. Please note that the device is *not* intended for use on human beings and must *not* be used in critical applications. Always observe the applicable safety requirements, especially when working with devices like lasers.

The CCD camera is suitable for desktop applications as well as notebook / laptop and mobile measurement applications. It can be used to capture images at a high optical resolution in 1-D and even in 2-D (by parallel moving of the CCD or the light source).

2.3. Ease of Use vs. Advanced Features

We have designed the CCD-S3600-D(-UV) to combine ease of use with unique and powerful advanced features. The device can be used by both types of customers:

- **novice users** who need to simply acquire light intensity data
- **advanced users and experts** who want to “squeeze out” each of the unique powerful features of the CCD device

2.3.1. Ease of Use for the Novice User

If you are a **novice user** you will probably just want to acquire light intensity data. In this case it is only required to set up the integration time, i.e. for how long the sensor will collect light during a scan. And that's all you need to start with data acquisition. Optionally, you may also want to choose how many scans you want to collect. There is no need to understand all details of CCD operation or the advanced operating modes in order to use the device for such basic tasks. You can just leave all advanced settings at their default values. A good starting point are the included LabVIEW examples and applications.



2.3.2. Unique & Powerful Features for the Advanced User

If you are an **advanced user** you will probably want to make use of the advanced features of the device. Some of those features include:

- Five CCD operating modes: Three internally synchronized modes with software capture start, hardware capture start, hardware capture enable; a special single shot mode and an external synchronization mode
- The external trigger input can be used to trigger a complete acquisition or to capture single frames selectively
- In external synchronization mode the external trigger input is used to synchronize frames and to define the integration time
- Integration time and other timing parameters can be set in very precise 1 μ s steps
- Hardware dark correction can be enabled if desired
- The device can give feedback through the trigger output when the next integration period will actually begin (even a couple of μ s in advance); this way the user can trigger external devices from the CCD or trigger a capture on the CCD itself from external devices at the right moment
- An unlimited number of subsequent frames can be streamed directly to the hard drive of the host computer; this is needed if the large onboard frame storage of 32 MB (4599 frames) is not enough for your needs

If you are an expert, you will be probably also interested in how the device works “under the hood”, e.g. how the integration time defines frame duration and frame rate. Or maybe you want to program the device yourself from your favorite programming language? For all of those advanced use cases you will find useful information and hints in the next chapters of this manual.

2.4. Features of the CCD Line Camera

The main hardware components of the CCD-S3600-D(-UV) line scan camera are (also refer to Figure 2-1):

- CCD (charge-coupled device) sensor with 3648 active pixels
- Main CCD controller FPGA
- 16-bit precise analog-to-digital converter (ADC)
- Large 32 MB DDR2 onboard memory for data storage / buffering
- USB 2.0 controller for the PC interface
- Trigger input and trigger output




Figure 2-1: Simplified Block Diagram of the CCD-S3600-D(-UV)

The CCD-S3600-D(-UV) features a **high-sensitivity linear CCD sensor** array with a large number of pixels (3648 active pixels), high optical resolution, wide spectral range from 320 nm to 1100 nm or 200 nm to 1100 nm with UV option as well as wide dynamic range.

The whole CCD line camera is controlled by an **advanced hardware controller** implemented in state-of-the-art FPGA technology, optimized for true high-speed parallel operation in hardware. FPGA technology has many benefits over microcontroller-based solutions used by other companies.

Sensor data is sampled using a high-end fast **analog-to-digital converter (ADC)** with precise **16-bit resolution** delivering 65536 possible intensity values for each CCD pixel.

For maximum flexibility, all parameters are **fully programmable** at runtime through software commands.

The **integration time** can be set in very precise 1 microsecond (μs) = 0.001 millisecond (ms) steps and it is programmable in the extremely wide range from 10 μs to one minute. This range applies to internal as well as external synchronization. In internal synchronization mode the internal timing module of the camera specifies the integration time. In external synchronization mode the external trigger signal provided by the user determines the integration time.

The device features **high frame rates** of up to 269.5 Hz with no missing frames. As with all CCD sensors, the actual frame rate depends on the set integration time.



There are two data storage modes: In the first mode, the device uses the large **32 MB DDR2 RAM for onboard storage** of up to 4599 frames during an acquisition; these frames can be fetched later by the host PC. The second mode is unique and allows the device to **stream an unlimited number of frames directly to the host PC**. This can continue for an unlimited amount of time, at the highest frame rate and again without any missing frames, being only limited by the storage device used. In addition, this sophisticated technology **uses the 32 MB DDR2 RAM to buffer frames** for up to 17 seconds (at the highest frame rate), before the host PC fetches that data. This enables reliable data streaming, even if the operating system becomes busy for some time. The extremely large 32 MB of high-speed RAM and the streaming mode are unique features that allow the user to capture an unlimited amount of subsequent frames back-to-back with no missing frames. In contrast, other manufactures offer just a few KB of RAM for frame storage on their devices.

The CCD line camera features **five different main operating modes** allowing internal or external frame synchronization, as well as internal or external triggering. Each of the five operating modes can be used together with onboard data storage mode as well as data streaming mode.

The gold-plated SMB **trigger input** can be used to trigger or to synchronize the CCD line camera from external devices. Depending on the selected operating mode, the trigger input is the acquisition start signal, the selective frame capture enable signal, the single shot trigger or the external synchronization signal.

The gold-plated SMB **trigger output** can be used to trigger or synchronize external devices from the CCD line camera (with 500 ns resolution). In most operating modes, this signal indicates to the user when the integration in a frame actually begins.

A **trig out before integration offset** can be also programmed to let external devices “know” in advance, when integration will actually start. The trigger output can be even used in combination with the trigger input in order to trigger an external device first, that finally triggers the CCD itself.

The **onboard hardware dark correction** uses the optical black pixels of the sensor and features temperature adaptability. It can be turned on or off at any time by the user.

Although the CCD-S3600-D(-UV) includes so many advanced features, it is **very compact and lightweight**. Only **modern highly-integrated, high-speed, low-power hardware components** from industry leading manufacturers have been implemented. The device contains **no moving parts**.

No external power supply is needed; power is provided **through the USB cable** for true single-cable plug & play operation. This makes the CCD camera ideal for mobile and notebook applications.



The high-speed **USB 2.0** (480 Mbit/s) interface connects the CCD-S3600-D(-UV) to the host computer. The USB controller is a dual-channel high-speed USB 2.0 chip from the industry leader FTDI (www.ftdichip.com).

Multi-OS support is a key feature in today's rapidly changing computer environments. For maximum compatibility at the USB level, the CCD camera uses the **original FTDI D2XX USB drivers** which are available free of charge and support **all major operating systems** including Microsoft **Windows** (XP, Vista, 7, Server 2003, Server 2008, Server 2008 R2 and future Windows versions) as well as **Linux**, Apple's **Mac OS X** and Microsoft's **Windows CE**. Both, **64-bit and 32-bit** operating systems are supported. Windows drivers also feature Windows Hardware Quality Labs (**WHQL**) certification. On operating systems like Windows 7, Vista and XP the driver is provided by the OS through Windows Update and installation is done **automatically by the OS without the need for manual driver installation** allowing true plug & play operation. The company FTDI is constantly updating the drivers to support new operating systems. For an updated list of operating systems compatible with the latest FTDI drivers, please see the FTDI web site.

The CCD-S3600-D(-UV) can be programmed and controlled through various programming languages and software development platforms like **LabVIEW, Visual C++, GCC C++, C++ Builder, C#, Delphi, Visual Basic, Java, LabWindows/CVI, Perl, Python**, etc. Because of this large variety of programming languages and platforms, ALPHALAS cannot support all of them directly, but customers can always refer to the programming examples and documentation on the FTDI web site for more information on their favorite programming language and platform.

Fully functional LabVIEW drivers, GUI applications and examples are included with the CCD-S3600-D(-UV) free of charge. The LabVIEW drivers have been developed according to the National Instruments driver guidelines. LabVIEW versions 8.6 and later are supported; for older versions please contact ALPHALAS. LabVIEW for Windows, Linux and Mac OS X is supported. The applications and examples include full data acquisition and data streaming applications as well as simultaneous acquisition with multiple line cameras connected to the same host computer. Additional examples demonstrate Gaussian fit, FWHM, 3D graph visualization, etc.

Fully functional free C++ source code is provided, demonstrating the CCD-S3600-D(-UV) in use. A complete project for Microsoft Visual C++ for Windows is included. This project is also compatible with the free Express edition of Visual C++. The same C++ source code can be also compiled directly with GCC (GNU Compiler Collection) for Linux, Mac OS X, etc. This application demonstrates that cross-platform development and access to the CCD device is possible.



The FTDI D2XX USB drivers include free **high-level USB interfacing libraries** for Windows (.dll), Linux (.so), Mac OS X (.dylib), etc. Communication to the onboard USB 2.0 controller can be established through simple **library function calls**. The driver's library interface hides the complex details of low-level USB communication (e.g. endpoints, descriptors, synchronization, etc.).

The CCD line camera is ideally suited for **OEM applications**. On the one hand, this is achieved by the compact and flexible hardware. On the other hand, this is achieved by the underlying flexible and open software development concept. Many companies modify USB drivers just to make their devices show up with a customized manufacturer's name. In contrast, ALPHALAS does *not* modify the original FTDI USB drivers. The benefit is that the device uses the standard widely used and certified drivers with the standard FTDI VID (vendor ID) & PID (product ID) and consequently ensures compatibility with all operating systems and programming languages supported by the driver **out of the box**. The customer also benefits from **all future free driver updates** and **new operating system support** from the industry leader FTDI. An additional benefit is that the device can be interfaced and programmed directly through all supported programming languages. It is not tied to some proprietary software package as this is the case with other manufacturers. This distinctive flexibility makes the CCD-S3600-D(-UV) ideally suited for research and OEM applications in diverse IT environments and also guarantees compatibility with future operating systems, hardware and software platforms.

Unlimited post-processing possibilities can be applied to the acquired data when using additional software packages like LabVIEW, MATLAB, Origin, Mathcad, etc. Instead of limiting the possibilities to a manufacturer's proprietary software package, this approach guarantees maximum flexibility for the customer's application and is especially important for research and OEM applications: Captured data can be processed by the user's own application without limitations. Post-processing can include **averaging, binning, accumulation, reference subtraction (all with floating point accuracy), noise removal, smoothing, function fitting and peak finding can be applied, data can be reviewed, zoomed in or out, printed, exported, converted to graphics, etc.** On a powerful PC with lots of memory much better post-processing can be performed than in hardware on the CCD camera itself. Data can be simply stored after acquisition and can be loaded later for further processing. Post-processing functionality is limited only by the capabilities of the user's software package.

The **signal-to-noise (SNR) can be improved (i.e. increased) by averaging multiple subsequent scans**. The SNR improves by the square root of the number of averaged scans. For example, the SNR improves by a factor of 10 when 100 scans are averaged. Averaging has been already built into the LabVIEW drivers.

Multiple CCD line cameras are supported on a single host computer. This allows the user to connect more than one device and acquire data from all devices simultaneously. An example application for LabVIEW is provided.



3. Specifications

3.1. Detailed Specifications

Please note: All specifications are typical at 25 °C unless otherwise stated. All specifications in this manual are subject to change without notice. No responsibility for typing or printing errors. All trademarks are the property of their respective owners.

| Parameters | Specifications | Notes |
|-------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Sensor Type | High-Sensitivity Linear CCD Array | Large number of pixels, high optical resolution and wide spectral ranges. |
| Active Sensor Pixels | 3648 pixels | |
| Total Sensor Pixels | 3694 pixels | Include optical black (light shielded) pixels and dummy pixels. |
| Size of Sensor Pixels (W x H) | 8 μm x 200 μm | The sensor features vertically elongated pixels for high sensitivity. |
| Active Length of Sensor | 3648 x 8 μm = 29.184 mm | |
| Spectral Range (typ.) | <ul style="list-style-type: none"> 200 nm - 1100 nm with UV option 320 nm - 1100 nm without UV option | The UV option must be ordered explicitly. |
| Dynamic Range (typ.) | 1000 : 1 | |
| Signal-to-Noise Ratio without Averaging (typ.) | 300 : 1 | Can be greatly increased by signal averaging. |
| Sensitivity (V/(lx*s)) (typ.) | 160 | High sensitivity CCD sensor. |
| Integration Time (T_{int}) | 10 μs – 1 minute, programmable in precise 1 μs (0.001 ms) steps | The integration time is controllable in an extremely wide range and in very precise steps. The same wide range is also usable with external synchronization triggering. |
| Frame Rate | Max. 269.5 Hz (frames/s) constant frame rate, corresponds to a minimum frame duration of 3710 μs (3.71 ms) | The frame rate depends on the set integration time. In streaming mode a constant frame rate without any missing frames can be achieved for an unlimited time. |
| Sensor Readout Time | 3710 μs (3.71 ms) | This time is specified by the sensor. |
| Sensor Modes | Shutter Mode for $T_{\text{int}} < 3710 \mu\text{s}$ Non-Shutter Mode for $T_{\text{int}} \geq 3710 \mu\text{s}$ | The CCD camera automatically uses the correct sensor mode. |
| Trigger Input | Yes | External devices can trigger the CCD. |
| Trigger Output | Yes | The CCD can trigger external devices. |
| Analog-to-Digital Converter (ADC) | 16-bit ADC | Industry-leading ADC, high-speed, high-precision, low-noise, low-power |
| Bits per Pixel | 16 bits / pixel | |
| Saturation Levels per Pixel | 65536 | |
| Pixel Output Speed | 1 MHz (1 μs / pixel) | |



| | | |
|----------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Readout Data Rate from Sensor to Internal RAM | 2 MBytes / s | |
| On-Board Memory | 256 Mbits (32 MBytes) High-Speed DDR2 RAM @ 266 MHz | The extremely large high-end DDR2 RAM runs at 266 MHz and is used for onboard data storage as well as for buffering in data streaming mode. |
| Data Acquisition Modes | <ul style="list-style-type: none"> • Onboard data storage mode (PC can fetch data later when free) • Data Streaming Mode (PC fetches data immediately, number of frames is not limited by the onboard RAM) | The unique data streaming mode allows the user to stream an unlimited amount of data to the PC at the highest frame rate without any missed frames. The only constraint is the data storage device (e.g. PC hard drive). |
| Onboard Data Storage | Up to 4599 frames can be captured, before fetching any of them. | The CCD can store up to 4599 frames onboard (approx. 17 s at the highest frame rate), before the PC fetches them. For <u>unlimited</u> number of captured frames see data streaming mode. |
| Data Streaming | <u>Unlimited</u> number of frames can be streamed to the PC in this mode. The large RAM is used as a FIFO frame buffer. | This mode allows capturing of an <u>unlimited</u> number of frames in real-time and streaming them directly to the PC's hard drive. The onboard RAM is used as a big buffer in this mode. |
| Continuous Frame Capture at Highest Frame Rate without Any Missing Frames | <ul style="list-style-type: none"> • <u>UNLIMITED</u> number of frames & capture time in data streaming mode • 4599 frames in onboard storage mode | Unique streaming technology with 32 MB RAM can buffer up to 17 s at the highest frame rate. This allows the PC to fetch the data on time. |
| Trigger Types | Internal & External Triggering | See operating modes below. |
| Main Operating Modes | Five main operating modes: 1. Internally synchronized, continuously running, with software capture start 2. Internally synchronized, continuously running, with hardware capture start 3. Internally synchronized, continuously running, with hardware capture enable 4. Single-shot with external hardware trigger (sensor is kept clean & ready), usable for T_{int} up to 500 μ s 5. Externally synchronized, continuously running, with software capture start | Each operating mode is usable in onboard data storage mode as well as data streaming mode |



| | | |
|---------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| External Trigger Input | Yes, gold-plated SMB connector. Used in the different operating modes as capture start, capture enable, single-shot trigger or synchronization trigger. | TTL, max. + 5 V (rising edge). Note: To be able to also capture short signals, the input signals are stretched by ~ 50 ns. The minimum trigger pulse width is ~ 8 ns. |
| External Trigger Output | Yes, gold-plated SMB connector. Used for synchronization of external devices. In most operating modes this signal indicates when the integration in a frame actually begins. In external synchronization mode this signal indicates when the integration in a frame ends. | TTL, + 5 V (rising edge). This signal is high for 500 ns. This means that external devices can be triggered with a resolution of 0.5 μ s when triggering on the rising or falling edge. |
| User-Definable Offset for Trigger Output Before Integration Starts | Yes, for short integration times when the sensor is in shutter mode. Programmable at runtime in the range from 0 μ s to 1849 μ s. | |
| Main CCD Controller Hardware | Industry-leading Xilinx FPGA for precise concurrent hardware control | |
| Full Programmability | Yes, all parameters are fully programmable at runtime through software commands. | |
| Onboard Signal Conditioning | Yes | |
| Onboard Dark Correction in Hardware | Yes, with temperature adaptability. | Can be activated by the user at any time. |
| PC Interface | High-Speed USB 2.0 (480 Mb/s) | USB Type B Connector on device side. |
| Onboard USB 2.0 Hardware | Industry-leading FTDI dual-channel high-speed USB 2.0 controller with FIFO buffers | |
| USB Bus Powered | Yes, no external power supply required. | Ideal for mobile & notebook applications. |
| Package Features | Very compact, no moving parts. | Ideal for mobile & notebook applications. |
| Plug & Play | Yes, plug & play operation. | Ideal for mobile & notebook applications. |
| OEM | Yes, ideal for OEM applications. | Very compact. Uses standard FTDI drivers & libraries. Multi-OS support. |
| USB Drivers & Libraries Included | Yes, FREE! Original FTDI drivers & libraries for high-level USB interfacing from multiple programming languages for Windows (.dll), Linux (.so) and Mac OS X (.dylib). WHQL certified. | FTDI D2XX drivers support all major operating systems & are constantly updated. Application software can access the USB device through simple high-level library function calls. No need to handle the low-level details of USB operation. |
| LabVIEW Drivers, GUI Applications & Examples Included | Yes, FREE! For LabVIEW 8.6 and later. Support LabVIEW for Windows, Linux and Mac OS. Compliant with NI driver guidelines. | Drivers, GUI applications and examples for data acquisition, data streaming, Gaussian fit, FWHM, 3D graph visualization, etc. |
| C++ Examples | Yes, FREE! Visual C++ project & GCC C++ files. Source code can be compiled under Windows, Linux and Mac OS X. | Well-commented source code demonstrates cross-platform access to the CCD device. Visual C++ Express is also supported. |



| | | |
|------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Post-Processing Possibilities with Additional Software Packages | Unlimited, using your favorite software package, e.g. LabVIEW, MATLAB, Origin, Mathcad, etc. | The captured data can be further processed using floating point accuracy (averaging, binning, accumulation, reference subtraction), noise can be removed, data can be reviewed, printed, exported, etc. This functionality is defined by the capabilities of your software package. |
| Programming Languages for Programming and Controlling the CCD | LabVIEW, Visual C++, GCC C++, C++ Builder, C#, Delphi, Visual Basic, Java, LabWindows/CVI, Perl, Python, etc. | The large variety of languages is not directly supported by ALPHALAS. Please refer to the programming examples on the FTDI web site (www.ftdichip.com) for more information. |
| Operating Systems Supported by the FTDI Device Driver | Microsoft Windows (XP, Vista, 7, Server, etc.), Linux (e.g. Ubuntu, openSUSE, Debian, etc.), Apple Mac OS X , Microsoft Windows CE 4.2-5.2 & CE 6.0. 32-bit & 64-bit OS are supported. | Windows Hardware Quality Labs (WHQL) certification. Fully automatic driver installation on plug-in through Windows Update. For an updated list of new operating systems compatible with the FTDI drivers, please see the FTDI web site (www.ftdichip.com). |
| Multi-Camera Support | Yes, multiple CCD line cameras are supported on the same host computer. | This allows the user to connect more than one CCD line camera and acquire data from all devices simultaneously. A LabVIEW example application is provided. |
| Visual Indicators | Power LED, Error LED | The Error LED will signal an internal buffer overflow in data streaming mode. |
| Host PC Hardware Requirements | Modern PC or Notebook (e.g. Intel Core CPU), 2 GB of RAM or more, USB 2.0, enough hard drive space if data streaming will be used. | The device should also run without problems on slower hardware. |
| Power-Up Time (Typ.) | < 1 s | |
| Operating Temperature | 0°C to 40°C | |
| Storage Temperature | -20°C to 60°C | |
| Relative Humidity | 0% to 80%, non-condensing | |
| Physical Dimensions (W x H x D) | ~ 90 x 25 x 105 mm See mechanical drawing. | Very compact size. |
| Weight | ~ 165 g | Very lightweight. |

3.2. Spectral Sensitivity






Figure 3-1: Spectral Sensitivity Chart

3.3. Connectors and Indicators on the Rear Panel



3.4. Mechanical Drawing



4. Description of Operation

4.1. Overview of CCD Operation

4.1.1. Collecting Light & Data Flow in the CCD-S3600-D(-UV)

The single line CCD sensor contains a photoactive region which is a linear array of individual pixels. These pixels are sensitive to light and accumulate electric charges which are proportional to the light intensity and the light exposure time. Those charges are then converted to digital light intensity values through the analog-to-digital converter (ADC). As soon as an acquisition has been initiated by the host PC, the acquired data is stored in onboard RAM and finally sent to the PC through USB (see Figure 4-1).




Figure 4-1: CCD Collecting Light and CCD Data Flow

4.1.2. Sensor Pixels

The CCD sensor consists of a large number of optical active pixels which collect usable light intensity information. The 3648 optical active pixels are situated in the middle of the sensor. At the beginning and at the end of the CCD sensor there are some dummy pixels. Most of the dummy pixels do not deliver usable information; only the optical black (light-shielded) pixels are used as a reference for dark correction. See Figure 4-2.




Figure 4-2: Pixels on the CCD Sensor

4.1.3. Exposure to Light and Integration Time

When the CCD sensor is exposed to light, this light causes each pixel to act as an accumulator of electric charge proportional to the light intensity and the time of exposure at that pixel (see Figure 4-3).




Figure 4-3: CCD Sensor Collecting Light

The converted into voltage light intensity values from each active pixel are then converted to digital data and sent to the PC. One set of light intensity data is often described as a frame, scan or readout.

As mentioned above, the voltage equivalent of the collected light also depends on the **time of exposure** to light. In order to define for how long the pixels of the CCD sensor will be exposed to light and accumulate charges, the **integration time** (T_{int}) must be specified.

Integration Time (T_{int}):

The integration time defines (in μs) for how long the sensor accumulates charges during a frame when exposed to light.

For very high integration times the pixels may collect too much light, become overexposed and saturated; they will then contain maximum digital intensity values (see Figure 4-4).




Figure 4-4: Integration Time and Overexposure

Overexposure should be avoided. If the sensor becomes overexposed, it may deliver incorrect intensity data, also in regions that are not overexposed. This is because excess charges from over-saturated pixels may propagate into adjacent pixels (blooming) or even the next frames. Therefore, make sure that the signal level stays below approx. 85% of the full digital range, i.e. 85% from 65535 \approx 55705.

All CCD sensors are sensitive to temperature. Therefore, especially for long-term measurements the device should be connected for approximately 10 minutes before starting the measurement and the ambient temperature should be kept constant during the measurement.

4.1.4. Attenuation of Light

The CCD camera has been calibrated to work with the shortest possible integration times (down to 10 μ s). This means that the CCD sensor will quickly become saturated when longer integration times are used. However, this is no big problem as light can be attenuated before it reaches the sensor.

This **attenuation** can be achieved by using an **optical filter** or a **polarizer** in case the light source is polarized. In the latter case, a combination of a **polarizer and a half wave plate** can be also used. This method offers the advantage of continuous adjustment of the light intensity from zero to maximum.




Figure 4-5: Light Attenuation

4.1.5. Damage Threshold of the CCD Sensor

Especially when working with powerful laser sources, care must be taken to prevent damage to the CCD sensor. Unfortunately, the manufacturers of CCD sensors do not provide exact data about damage thresholds. However, one thing is clear:

The sensor will become saturated far earlier than the damage threshold is reached.

Therefore, the following rules should be followed:

Never shoot directly with a laser onto the sensitive area of the CCD.

The best way to work safely with the sensor is to start with a strong attenuation of the light source and gradually decrease this until a good signal is achieved.

Remember that increasing the integration time may lead to earlier saturation of the signal.

From a general point of view, power of more than 1 W/cm² CW and pulse energy of 0.1 μ J/cm² (at 10 ns) must be avoided. But as stated before, with these values the sensor will be already heavily oversaturated.

4.1.6. Frames, Sensor Readout and Continuously Running Frame Integration

So far, we have considered only the **integration** of a *single* frame (also called scan or readout). Charges proportional to the light intensity as well as to the exposure time have been collected in the sensor as soon as the integration of that frame is complete; but these charges *still* have *not* been read out from the sensor. This sensor readout has to be done *after* integration of the current frame has finished. As soon as the integration for one such **frame is complete**, the **charges from all pixels** are first **transferred at once into a transmission region** on the sensor – the **analog shift register**. From there, the sensor will output them one by one and they can be sampled by the analog-to-digital converter (ADC), then stored in onboard RAM as digital values and finally transferred to the PC (again refer to Figure 2-1 and Figure 4-1).

Typically, the CCD operates in such a way that it does **not** integrate single frames only and does **not** have to “wait” for them to be read out before starting a new frame. Instead, it **continuously** integrates frames back-to-back. While the charges from the previous frame are being read out, the CCD-S3600-D(-UV) can already integrate the next frame, i.e. the sensor again starts to collect light. This has the advantage that the pixel charges collected during the **last** frame can be read out from the sensor and saved while the **next frame** is being integrated **in parallel**. This allows continuous acquisition of multiple frames back-to-back with **no dead time between frames**. See Figure 4-6.




Figure 4-6: Continuous Frame Integration and Readout in Parallel

This **continuously running frame integration** starts immediately as soon as the CCD device has been powered up or reconfigured. The device begins to continuously integrate frames back-to-back and without stopping. This operation is already in progress even before an acquisition has been initiated. During each frame, the CCD sensor is collecting light for the same amount of time, which is defined by the **integration time** parameter. All frames have the same duration. There is no gap between frames – as soon as a frame finishes, the next frame immediately starts and so on.



Please note that data from those continuously running frames will be **only then stored for further use**, if an acquisition has been started, otherwise that data is simply discarded.

In detail, the following happens between two frames:

1. As soon as the **exposure for the current frame has finished**, the **exposure for the next frame immediately begins**. The sensor again starts to collect light.
2. **At the same time (at the start of the new frame), the individual pixel charges collected during the previous frame are immediately transferred at once into the transmission region** of the sensor and now start being **shifted out on a one-by-one (pixel by pixel) basis** from the analog shift register. This process is called **reading out the sensor**. Each shifted out pixel charge goes through an amplifier circuit and is converted into a voltage. This voltage is then converted through the ADC (analog-to-digital converter) to digital data which represents the light intensity value for the individual pixel. **If an acquisition has been started by the host PC, the digital data is immediately stored into internal device memory; otherwise it is simply discarded.** Later, the digital data can be fetched from the internal device memory and transferred to the host PC.

This means that the **readout of a previous frame overlaps with the exposure of a new frame**. Readout is done by sampling the voltage of each individual pixel and therefore takes some time. The total sensor readout time is proportional to the number of pixels and equals **3710 μ s** (3.71 ms) for the CCD-S3600-D(-UV). This readout time is defined by the sensor hardware.

Sensor Readout Time (T_{readout}):

The sensor read out time is the time required to read out all collected pixel charges from the last frame. It is constant. For the CCD-S3600-D(-UV) this time is 3710 μ s (3.71 ms).

4.1.7. Integration Time vs. Readout Time, Non-Shutter Mode vs. Shutter Mode

As previously described, because of the continuously running frame integration of the CCD, **during each frame two things happen at the same time**:

1. The **integration** of the **current** frame takes place. The specified **integration time** defines for how long the sensor will collect light during that frame and therefore obviously, **how long the frame will last**.
2. The **readout** of the **previous** frame takes place. The sensor readout time is defined by the sensor hardware and is 3710 μ s (3.71 ms).



Because of the fact that the readout of all pixel values from the previous frame takes place **while** the new frame is being exposed to light, **the frame duration cannot be below the readout time** of the sensor. Because of this readout time restriction of 3.71 ms, it is obvious that **a frame cannot be shorter than 3710 μ s (3.71 ms)**. Otherwise the sensor would not be able to readout all pixel charges from the previous frame. **It is important to understand that a full readout must be done after each frame in order to clean the sensor for the next frame.** This means that even if the user does not need the data from a frame, the readout still **must** be done after each frame, in order to clear the analog shift register from the accumulated charges and ensure that it is empty for the next frame. This will make sure that the **sensor is clean** for light exposure in the new frame and does not contain charges from the previous frame.

Sensor Readout Time Restriction:

A frame cannot be shorter than the sensor readout time of 3710 μ s (3.71 ms).

This restriction would normally imply that the integration time also cannot be set below the readout time of 3710 μ s. Fortunately, the CCD-S3600-D(-UV) device uses an advanced CCD sensor, allowing **integration times down to 10 μ s**. This is achieved by using the special **shutter mode** of the sensor which will be described shortly. But first, the normal **non-shutter** mode will be described.

Non-Shutter Mode

This mode is used whenever the **integration time is equal to or greater than the sensor readout time** of 3710 μ s. In this case, the frame readout time restriction does not pose a problem and the frame duration always equals the integration time. See Figure 4-7.




Figure 4-7: Frames with Integration Time \geq Readout Time : Non-Shutter Mode

Shutter Mode

The next question is what happens if the integration time is set to a value below the sensor readout time of 3710 μs ? In this case the device will automatically drive the sensor in the special **shutter mode**. This is again required by the sensor hardware:

Integration Times Below the Readout Time:

When the integration time is shorter than the sensor readout time of 3710 μs (3.71 ms), the integration time will be repeated multiple times in a frame, until the frame time becomes equal to or greater than the sensor readout time. The frame duration then equals that least multiple of the integration time.

Only the last integration time period in the frame will take effect because the shutter will clear all collected charges whenever a new integration time period starts during a frame.

Shutter mode is shown in Figure 4-7.

In shutter mode the integration time is repeated **M times** during a frame, until the frame time becomes equal to or greater than the sensor readout time of 3710 μs . Here $M = 3$.




Figure 4-8: Frames with Integration Time < Readout Time : Shutter Mode

In shutter mode only the last part of the frame is used for integration; this way integration times below the sensor readout time can be used, but the minimum frame duration is still the sensor readout time.

When working with pulsed lasers, the laser pulse should appear immediately when the actual integration begins, i.e. at the beginning of the last integration time period in the last part of the frame. This gives the most accurate results. The trigger output feature of the CCD-S3600-D(-UV) can be used to trigger the laser as described in details in the next chapters.



4.1.8. Integration Time vs. Frame Rate

The **integration time** will influence:

1. **how long a single frame** will last
2. the **frame rate**

The frame rate (or line scan frequency) is inversely proportional to the integration time.

In **non-shutter mode** ($T_{int} \geq 3710 \mu s$):
 The frame duration equals the integration time.
 The **frame rate** equals $1/T_{int}$.

In **shutter mode** ($T_{int} < 3710 \mu s$):
 The frame duration equals the least multiple M of the integration time, where
 $M * T_{int} \geq T_{readout}$.
 $T_{readout}$ is the sensor readout time and equals 3710 μs .
 The **frame rate** equals $1/(M * T_{int})$.

The following table lists some **frame rates** that can be achieved for different **integration times** with the CCD-S3600-D-(UV):

| Integration Time T_{int} (μs) | T_{int} Period is Repeated in Frame (times) | Resulting Frame Duration (μs) | Resulting Frame Rate (Hz) |
|---------------------------------------------------------------------------|-----------------------------------------------|--------------------------------------|--------------------------------------------|
| $T_{int} < T_{readout} \rightarrow$ Shutter Mode | | | |
| 10 | 371 | 3710 | ~ 269.5 |
| 50 | 75 | 3750 | ~ 266.7 |
| 100 | 38 | 3800 | ~ 263.2 |
| 500 | 8 | 4000 | 250 |
| 1000 | 4 | 4000 | 250 |
| 2000 | 2 | 4000 | 250 |
| $T_{int} \geq T_{readout} \rightarrow$ Non-Shutter Mode | | | |
| 3710 and above | 1 | = T_{int} | = $(1 / T_{int}) * 10^6$ |



4.1.9. Integration Time with Internal vs. External Synchronization Mode

There are two ways to define the integration time:

The first is when using **internal synchronization**. In this mode the user sets the integration time through a software command and this value is used by the internal timing module of the device to automatically define the exposure period as well as when a frame will start and when it will end. Internal synchronization is used in most CCD operating modes described later in chapter 4.3.

The second option to define the integration time is **external synchronization**. In this mode an external synchronization pulse with a constant period will be applied to the trigger input of the device and the time between external trigger pulses will determine the integration time as well as when a frame starts and when it ends. External synchronization is used only in externally synchronized operating mode described later in chapter 4.3.

So far we have described what frames are, how the integration time parameter defines the exposure to light during a frame and how the sensor is read out. Next we will describe further details of CCD operation.

4.2. Configuration and Acquisition

Whenever the CCD device is powered up, it starts in its default configuration. The default configuration presets the device to factory default modes and parameters. For example, the default integration time is preset to 5000 μ s.

In most operating modes, the CCD immediately starts to integrate frames back-to-back and therefore enters continuously running frame integration. The first frame of that sequence is an **initial dummy frame** during which any old charges are read out from the sensor but the data is simply discarded. The data collected during the initial dummy frame is also discarded when it is read out during the next frame. Data collected during the frame **after the initial dummy frame** as well as during next frames can be captured and stored, but only if an acquisition has been started. See Figure 4-9.




Figure 4-9: Initial Dummy Frame after Power Up or Reconfiguration

Although the CCD is continuously running and integrating frames, as long as there is no acquisition in progress, any read out frame data is discarded instead of being stored or transferred to the PC.

As long as there is **no** acquisition in progress, the CCD will accept commands from the USB interface. Such commands can be configuration commands, commands to initiate an acquisition, etc.



4.2.1. Configuration

While there is no acquisition in progress, the device can be reconfigured by sending configuration commands from the host PC to the device via USB.

Configuration commands set the CCD parameters or modes to new values:

- Set integration time (in μs)
- Set frames (scans) per acquisition → use for onboard storage mode: 1 to 4599 frames
- Set CCD operating mode → five different modes (described in the next chapters)
- Set trig out before integration offset (in μs)
- Enable or disable hardware dark correction
- Include dummy pixels in readouts → this advanced command is normally not used

These configuration commands will be described later in details.

Whenever a valid configuration command is received, it will first reset the CCD, apply the new parameter, interrupt the current frame and start integrating new frames with the newly defined parameter by entering continuously running frame integration. The first new frame is a new initial dummy frame. During that initial dummy frame the device will readout any old sensor data and discard it. The data read out from the initial dummy frame is also readout and discarded during the next frame. Data read out during further frames will be stored if an acquisition is in progress. Again refer to Figure 4-9.

The device will additionally return an **ACK** (acknowledgement) byte to the host PC via USB as a reply to a successful configuration command. After reconfiguration, the device will again start accepting new commands.

If an **invalid command** is received, this command will be simply **ignored** and will not influence current CCD operation. The device will respond with a **NACK** (not acknowledged) byte reply to the host PC via USB.



4.2.2. Acquisition and Data Modes

After having configured the device, the user must send a special *initiate acquisition* command to the device in order to initiate an acquisition. This is required in order to be able to capture frames. However, in most modes, **initiating** an acquisition does not immediately *start* acquisition (i.e. the actual capturing of frames). In those modes an additional trigger is also required. This behavior depends on the selected operating mode and will be described later in details.

The *initiate acquisition* command is sent from the host PC to the CCD device via USB. There are actually two different commands that will initiate an acquisition, depending on the data mode the user wants to use:

- Initiate acquisition in onboard data storage mode
- Initiate acquisition in data streaming mode

Onboard Data Storage Mode

In this mode the device will store the captured frames into **onboard memory**. They can be fetched later by the host PC. As soon as acquisition starts, the device will capture the **set number of frames (scans) per acquisition** into onboard RAM. As soon as this has been done, **acquisition will finish automatically** and the device will send all captured frames to the host PC which is now responsible for fetching the data through USB. In this mode the number of required frames is set through the correspondent parameter and is limited by the onboard RAM to 4599 frames (which is a very large value and will be sufficient in most cases).

Data Streaming Mode

In this mode the device will **immediately stream** any captured data to the host PC. The data rate is very high and it is therefore not recommended to view the acquired data in real time. Instead, all saved frames can be viewed later from the hard drive of the host PC. There is no frame limit in this mode and data can be streamed without missing any frame. As soon as acquisition starts, the device will always **ignore the set number of frames (scans) per acquisition**. Instead it will stream any captured frames immediately to the host PC until the device **receives the *stop acquisition and data streaming* command** (or actually any other command) from the host PC. After receiving the stop command the device will capture one more frame and then stop acquisition. During streaming, the onboard RAM is used as a big FIFO frame buffer and prevents data overflow during capture. If there are any frames left in the buffer after acquisition is stopped, they will be still streamed to the PC.

Finishing Acquisition

In both data modes, after the final captured frame in the acquisition, the CCD will always do a **last readout-only frame**, during which the data from that last captured frame will be readout and stored. After that, the CCD will continue integrating new frames. These new frames will be always read out from the sensor but the data will be simply discarded until the next acquisition has been started. See Figure 4-10.




Figure 4-10: Finishing the Acquisition and Last Readout-Only Frame

Note: While acquisition is in progress the CCD will not accept new commands until the acquisition has finished.



4.3. CCD Operating Modes

In the last subchapter we discussed how an acquisition is initiated and when it finishes, depending on the data mode selected, i.e. onboard data storage mode vs. data streaming mode.

Initiating an acquisition is always required before frame capturing can start, but it only means that the CCD becomes ready for capturing and storing frames. Though, it does **not mean that the device will immediately start to capture and store frames**. *When* capture will actually occur, is defined by one of the five CCD operating modes.

After an acquisition has been initiated, the selected **CCD operating mode** will determine, **if** and **when** a frame will be actually captured and stored. It will determine **what will trigger** a capture. A capture can be triggered by software or by hardware.

The following operating modes are available on the CCD-S3600-D(-UV):

- **Internally synchronized, continuously running, with software capture start**
- **Internally synchronized, continuously running, with hardware capture start**
- **Internally synchronized, continuously running, with hardware capture enable**
- **Single-shot, clean & ready with external hardware trigger**
- **Externally synchronized, continuously running, with software capture start**

In all **internally** synchronized modes as well as the **single shot** mode the device uses its **internal timing** generator and the programmable integration time which is set by the user in order to generate frames.

In contrast, in **externally** synchronized mode the **external synchronization** signal will define the integration time and the frame duration.

In the **internally** synchronized modes as well as in **externally** synchronized mode the CCD enters **continuously running** operation and already starts integrating frames but still does not capture any frames until an acquisition has been initiated and actually started by the software or hardware trigger used in the corresponding mode.

In contrast, in **single shot** mode the sensor is kept clean and ready but does **not** enter continuously running frame integration. Instead, it waits for the hardware trigger to start integrating a frame.


Next, the five modes will be described in details.

4.3.1. Internally Synchronized, Continuously Running with Software Capture Start

This is the default and the simplest operating mode. In this mode **no external trigger** is required. **Acquisition starts** immediately as soon as the **initiate acquisition** command arrives.

In this mode the frame duration and synchronization is defined by the internal CCD controller clock and the set integration time. The CCD is in continuously running operation and integrates frames back-to-back, no frames are skipped.

Frame capturing starts **immediately** as soon as the **initiate acquisition command** arrives from the host PC via USB. The first captured frame is the frame that is currently being integrated when the initiate acquisition command arrives. No external trigger signal is used in this mode; therefore the capture start is software-defined. See Figure 4-11.



Note: In this example the user has set 5 frames (scans) per acquisition.

Figure 4-11: Internally Synchronized, Continuously Running with Software Capture Start

In **onboard data storage mode**, as soon as the acquisition is initiated, the set **number of frames (scans) per acquisition** are captured back-to-back. As soon as this is done, the acquisition will finish automatically.

In **data streaming mode**, as soon as the acquisition is initiated, the CCD starts capturing frames back-to-back and streaming them to the host PC. This will continue until the **stop acquisition and data streaming command** arrives from the PC.


In both data modes, integrated frames are read out and saved in the next frame as described in the previous chapters. In order to save the last frame, a final readout-only frame is needed.

4.3.2. Internally Synchronized, Continuously Running with Hardware Capture Start (Rising Edge Triggering)

This operating mode is very similar to the previously described operating mode, but allows the user to start the actual capture as soon as a **rising edge** appears on the external trigger input. All subsequent frames are then captured back-to-back, no frames are skipped.

In this mode the frame duration and synchronization is defined by the internal CCD controller clock and the set integration time. The CCD is in continuously running operation and integrates frames back-to-back.

Frame capturing does **not** start immediately when the initiate acquisition command arrives from the host PC via USB. Instead, the CCD will wait **until a rising edge appears on the external trigger input** during a frame. Therefore, the capture start is hardware-defined. The first captured frame is the frame that is currently being integrated when the trigger edge arrives. See Figure 4-12.



Note: In this example the user has set 5 frames (scans) per acquisition.

Figure 4-12: Internally Synchronized, Continuously Running with HW Capture Start

In **onboard data storage mode**, as soon as the trigger edge arrives, the set **number of frames (scans) per acquisition** are captured back-to-back. As soon as this is done, the acquisition will finish automatically. The trigger input is ignored until the end of this acquisition.

In **data streaming mode**, as soon as the trigger edge arrives, the CCD starts capturing frames back-to-back and streaming them to the host PC. This will continue until the **stop acquisition and data streaming command** arrives from the PC. The trigger input is ignored until the end of this acquisition.



In both data modes, integrated frames are read out and saved in the next frame as described in the previous chapters. In order to save the last frame, a final readout-only frame is needed.

Please note that **edge** triggering is used here, not level triggering. The CCD will wait for a rising edge on the trigger input signal.

The trigger input used in this mode can be synchronized with the trigger output from the CCD which indicates when the integration in a frame actually starts. For further information please refer to chapter 4.5.


If the CCD device does not receive a trigger input signal, the control software (e.g. LabVIEW) will appear frozen. If your device appears frozen, you may want to disconnect the device from the USB port of the host PC. This should make the software report a connection error and exit the waiting loop.

4.3.3. Internally Synchronized, Continuously Running with Hardware Capture ENABLE (High Level Triggering)

This operating mode allows the user to select **which** frames will be actually captured by using the level of the external trigger input. Only frames during which this external signal is **high** will be captured. Therefore captured frames do not have to be back-to-back, i.e. frames can be skipped intentionally.

In this mode the frame duration and synchronization are defined by the internal CCD controller clock and the set integration time. The CCD is in continuously running operation and integrates frames back-to-back.

Frame capturing does **not** start immediately when the initiate acquisition command arrives from the host PC via USB. Instead, the CCD will wait until a **high level** on the external trigger input appears. Therefore, the capture start is hardware-defined. The first captured frame is the frame that is currently being integrated when the high level on the trigger input is detected. **In this mode the trigger level is used to select which frames need to be captured = capture enable.** The captured frames do not have to be back-to-back. **Only subsequent frames during which the external trigger input signal is high will be captured.** In this mode, the external trigger signal is still being evaluated after having started capturing. See Figure 4-13.



Note: In this example the user has set 4 frames (scans) per acquisition.

Figure 4-13: Internally Synchronized, Continuously Running with HW Capture ENABLE

In **onboard data storage mode**, whenever a high level is detected on the external trigger input, the current frame will be captured, until the set **number of frames (scans) per acquisition** have been all captured (this does not have to be back-to-back). As soon as this number of frames has been reached, the acquisition will finish automatically. The trigger input will be watched for a high level until the end of this acquisition.



In **data streaming mode**, as soon as a high level on the external trigger input is detected, the CCD will capture the current frame and stream it to the host PC. This will continue until the **stop acquisition and data streaming command** arrives from the PC. The trigger input will be watched for a high level until the end of this acquisition.

In both data modes, integrated frames are read out and saved in the next frame as described in the previous chapters. In order to save the last frame, a final readout-only frame is needed.

Please note that **level** triggering is used here, not edge triggering. The CCD will watch for a high level on the trigger input signal.

The trigger input used in this mode can be synchronized with the trigger output from the CCD which indicates when the integration in a frame actually starts. For further information please refer to chapter 4.5.

If the CCD device does not receive a trigger input signal, the control software (e.g. LabVIEW) will appear frozen. If your device appears frozen, you may want to disconnect the device from the USB port of the host PC. This should make the software report a connection error and exit the waiting loop.



4.3.4. Single Shot, Clean & Ready with External Hardware Trigger (Rising Edge Triggering), Use for $T_{\text{int}} \leq 500 \mu\text{s}$ Only

This advanced operating mode allows the user to start the integration of a **new** frame as soon as an external **trigger rising edge** arrives. This behavior is different from the modes described so far, because it does **not** use continuously running frame integration. Instead, the device **keeps the sensor clean** by using the shutter. It does not integrate frames and does not collect charges, until the trigger arrives. When the trigger edge arrives, a **single** frame will be integrated. After that frame, the sensor is readout and the data is captured and stored. Then the sensor returns back to the clean & ready state waiting for the **next** frame trigger. Because of the readout phase and the clean & ready state between frames, captured frames cannot be back-to-back.

This single shot mode makes use of some very special properties of the CCD sensor. It is useful for pulsed lasers for example.


As soon as the device is set to this mode, instead of continuously integrating frames, the following happens: The device reads out the sensor first in order to clean it from previous charges (this takes $3710 \mu\text{s}$ and is comparable to the initial dummy frame in other modes). The device then enters the so called “clean & ready” state. In this state the CCD sensor does not collect charges but is **kept clean and ready** for the integration of a next single shot frame. This single shot frame is triggered as soon as a rising edge appears on the external hardware trigger input. After the integration of the single shot frame has finished, the device will read out the charges collected during that single shot frame (this takes again $3710 \mu\text{s}$) and then the device again enters the clean & ready state to wait for a next trigger.

Because of the special sensor behavior used in order to keep the sensor clean, this mode can be used **only for integration times $\leq 500 \mu\text{s}$** . Please note that for such $T_{\text{int}} \leq 500 \mu\text{s}$, the sensor will use shutter mode and the **integration will take place during the last T_{int} period of the frame!** The laser pulse should appear at the beginning of this integration period, in the last part of the frame. See Figure 4-8 as a reminder.

If integration times longer than $500 \mu\text{s}$ are specified, the captured light intensity values may become too low. For $T_{\text{int}} \leq 500 \mu\text{s}$ the error is typically $< 0.1\%$.

In this mode the frame duration and synchronization are defined by the internal CCD controller clock and the set integration time. The CCD is **not** in continuously running operation and will only integrate a single frame, as soon as the trigger arrives. Then it will clean the sensor first. Therefore, it will never capture frames back-to-back in contrast to the other operating modes.

Frame capturing does **not** start immediately when the initiate acquisition command arrives from the host PC via USB. Instead, the CCD will wait until a **rising edge** on the external trigger input appears while the sensor is in the clean & ready state. Then it will start the single shot frame that will be captured. Therefore, the capture start is hardware-defined. See Figure 4-14.



Note: In this example the user has set 2 frames (scans) per acquisition.

Figure 4-14: Single Shot, Clean & Ready with External Hardware Trigger

The external trigger signal will be ignored while the device is integrating the frame and reading out the sensor. As soon as it has reentered clean & ready state, the next trigger can capture the next frame if an acquisition is in progress.

In **onboard data storage mode**, as soon as the trigger edge arrives, a single frame will be started and captured, until the set **number of frames (scans) per acquisition** have been all captured (not back-to-back here). As soon as this number of frames has been reached, the acquisition will finish automatically. The trigger input will be watched for the next rising edge until the end of this acquisition, whenever the device has returned to the clean & ready state.

In **data streaming mode**, as soon as the trigger edge arrives, the CCD will start and capture a single frame and stream it to the host PC. This will continue until the **stop acquisition and data streaming command** arrives from the PC. The trigger input will be watched for the next rising edge until the end of this acquisition, whenever the device has returned to the clean & ready state.



In both data modes, the single integrated frames are read out and saved during the sensor readout-only phase of 3710 μ s after those frames. The frame data is also stored into RAM during that phase.

Please note that **edge** triggering is used in this mode, not level triggering. The CCD will wait for a rising edge on the trigger input signal.

If the CCD device does not receive a trigger input signal, the control software (e.g. LabVIEW) will appear frozen. If your device appears frozen, you may want to disconnect the device from the USB port of the host PC. This should make the software report a connection error and exit the waiting loop.



4.3.5. Externally Synchronized, Continuously Running with Software Capture Start

All operating modes described so far used internal synchronization. In those modes the user entered an integration time and this value was used by the internal timing module of the device to automatically define the exposure period as well as when a frame will start and when it will end.

In contrast, *this* mode uses **external synchronization**. An external trigger pulse **with a constant period** is applied to the trigger input of the device and the time between external trigger rising edges will determine the integration time period as well as when a frame starts and when it ends. **The external synchronization trigger edges should be set up to arrive continuously and with a constant period on TRIG IN before initiating an acquisition.** The minimum time between rising edges is 10 μs (= minimum integration time). The resulting integration time resolution will be 1 μs . The signal does not need to have an even duty cycle of 50%.

The integration time set by the user is completely ignored in this mode.

Besides the fact that this mode uses external synchronization, it is very similar to the default *internally synchronized, continuously running, with software capture start* mode. Acquisition starts **immediately** as soon as the **initiate acquisition** command arrives (software capture start). It is important to note, that in this mode the external signal applied to the trigger input is only used for continuous frame **synchronization**; it is **not** used to trigger specific frames.

In this mode the **integration time** as well as the **frame duration, frame synchronization and frame rate** are defined by the **rising edges** on the *external* trigger input. Actually the device will use special hardware algorithms to watch the time interval between the rising edges. If the time interval is $\geq 3710 \mu\text{s}$ the device will work in non-shutter mode and the next rising edge will always start a new frame. If the time interval is $< 3710 \mu\text{s}$ then the device will switch to shutter mode and multiple integration time periods will be repeated until the minimum frame duration of 3710 μs (= T_{readout}) has been reached. See chapter 4.1.7 as a reminder regarding shutter mode.

In this operating mode the CCD is in continuously running operation and integrates frames back-to-back.

Assumed that the external synchronization trigger is already running continuously as described above, frame capturing will start **immediately** as soon as the **initiate acquisition command** arrives from the host PC via USB. The first captured frame is the frame that is currently being integrated when the initiate acquisition command arrives. **No** external trigger signal is used to start capture in this mode; therefore the capture start is software-defined. See Figure 4-15.




Figure 4-15: Externally Synchronized, Continuously Running with Software Capture Start

Shutter mode details are shown in Figure 4-16. **Here the period between the rising edges of the external signal will define the integration time period.** The expired frame time is calculated on the fly and a new frame starts as soon as the expired frame time becomes equal to or greater than the sensor readout time.

In shutter mode the integration time is repeated **M times** during a frame, until the frame time becomes equal to or greater than the sensor readout time of 3710 μ s.




Figure 4-16: A Frame in Shutter Mode with External Synchronization

Please note that in shutter mode the frame rate does not equal the synchronization trigger rate any more. Multiple synchronization trigger edges occur during a single frame. Again refer to Figure 4-16.



In **onboard data storage mode**, as soon as the acquisition is initiated, the set **number of frames (scans) per acquisition** are captured back-to-back, assuming that the external synchronization trigger edges arrive continuously from the external trigger source. As soon as this is done, the acquisition will finish automatically.

In **data streaming mode**, as soon as the acquisition is initiated, the CCD starts capturing frames back-to-back and streaming them to the host PC. This will continue until the **stop acquisition and data streaming command** arrives from the PC.

In both data modes, integrated frames are read out and saved in the next frame as described in the previous chapters. In order to save the last frame, a final readout-only frame is needed.

If the CCD device does not receive a trigger input signal, the control software (e.g. LabVIEW) will appear frozen. If your device appears frozen, you may want to disconnect the device from the USB port of the host PC. This should make the software report a connection error and exit the waiting loop.



4.4. Connecting the Trigger Input Signal to the CCD

Four of the five CCD operating modes described in chapter 4.3 require the use of the external trigger input (the purpose of the trigger is shown in **bold** below):

- Internally synchronized, continuously running, with **hardware capture start**
- Internally synchronized, continuously running, with **hardware capture enable**
- Single-shot, clean & ready with **external hardware trigger**
- **Externally synchronized**, continuously running, with software capture start

So the trigger will be used either as the capture start, the capture enable, the single-shot trigger or the synchronization trigger in these modes.

The trigger input can be used to synchronize the CCD with external devices like pulsed lasers etc.

Connect an appropriate cable to the **TRIG IN** SMB connector on the CCD device. The external trigger signal must be **max. +5 V, TTL (rising edge)**. Most CCD operating modes are **rising edge triggered**, only the **internally synchronized, continuously running, with hardware capture enable** mode is **level** triggered, not edge triggered.

The minimum trigger pulse width is ~ 8 ns. To be able to capture short signals, all input signals are stretched in hardware by ~ 50 ns at + 5 V (by less than 50 ns for voltages below + 5 V).



4.5. Trigger Output from the CCD

The CCD-S3600-D(-UV) features a unique **trigger output** used to **trigger external devices** from the CCD. This signal can be used to synchronize external devices to the internal integration period of the CCD. In most CCD operating modes this signal indicates when integration actually *starts* in each frame. Due to the different behavior in external synchronization mode, in that mode the trigger output indicates when integration has actually *finished* for a frame.

The trigger output signal pulse stays at high level for 500 ns. If the external device can be triggered on rising and falling edge, a trig out precision of 500 ns can be achieved.

The trigger output is + 5 V, TTL (rising edge).

4.5.1. Trigger Output Indicating “Integration Start”

In the following **CCD operating modes** the trigger output signals **when the integration actually starts** in a frame:

- **Internally synchronized, continuously running, with software capture start**
- **Internally synchronized, continuously running, with hardware capture start**
- **Internally synchronized, continuously running, with hardware capture enable**
- **Single-shot, clean & ready with external hardware trigger**

Integration Start Output in Non-Shutter Mode

In non-shutter mode (i.e. $T_{\text{int}} \geq 3710 \mu\text{s}$) the trigger output (TRIG OUT) will always fire **at the beginning of the frame**, at the point in time when the actual integration period begins. The user definable **trig out before integration offset** is **ignored** in this mode and the offset is always $0 \mu\text{s}$ (otherwise the offset trig out signal would have to appear during the previous frame). See Figure 4-17.




Figure 4-17: Trig Out at Integration Start in Non-Shutter Mode

Integration Start Output in Shutter Mode

In shutter mode (i.e. $T_{int} < 3710 \mu s$) the trigger output (TRIG OUT) will fire **at the beginning of the effective integration period in the frame**, i.e. the last repetition of the integration time in the frame. See also chapter 4.1.7 as a reminder on how shutter mode works. The user definable **trig out before integration offset** can be used in this mode. A trig out offset before integration start can be specified in the range between **0 μs (= no pre-integration offset)** and **1849 μs (= max. possible pre-integration offset)**.

For an example with **0 μs offset** before integration start (i.e. no offset) see Figure 4-18.




Figure 4-18: Trig Out at Integration Start in Shutter Mode (No Offset)



For an example with an offset before integration start (from 1 μ s to 1849 μ s) see Figure 4-19.




Figure 4-19: Trig Out at Integration Start in Shutter Mode with Offset

In the following **CCD operating modes** the **trigger output** (TRIG OUT) may be used to **synchronize** an external device or system that will then assert the **trigger input** (TRIG IN) as **hardware capture start / enable** signal to start or enable capture in the current frame:

- **Internally synchronized, continuously running, with hardware capture start**
- **Internally synchronized, continuously running, with hardware capture enable**

See Figure 4-20.




Figure 4-20: Trig Out at Integration Start used Together with Trig In

In order to **capture the current frame**, one can assert TRIG IN **right after** the TRIG OUT rising edge. The assertion of TRIG IN must happen **at least 5 µs before the integration period expires**. This is required because of the way how the sensor integrates frames. For example, if the integration time is set to the absolute minimum of 10 µs (shutter mode used and integration takes place in the last 10 µs of the frame) and TRIG OUT uses no trig out offset, the TRIG IN should be asserted in less

than 5 μs after the TRIG OUT rising edge in order to start capture / enable capture in the **current** frame.

4.5.2. Trigger Output Indicating “Integration End”

In contrast to the CCD operating modes described so far, in the **externally synchronized, continuously running, with software capture start** mode the trigger output signals **when the integration actually ends** in a frame (not when it starts).

This different behavior is due to the fact that the integration time and frame duration are **not known in advance** in this mode; they are defined during runtime by the external synchronization trigger signal. Actually, there is no difference if non-shutter mode or shutter mode is used here. See Figure 4-21 for non-shutter mode and Figure 4-22 for shutter mode. An offset cannot be defined.




Figure 4-21: Trig Out at Integration End in Ext. Synch. Mode (Non-Shutter Mode)




Figure 4-22: Trig Out at Integration End in Ext. Synch. Mode (Shutter Mode)



4.6. Detailed Description of Commands and Programming

This chapter includes detailed description of the CCD commands with the required data values and their default values. It also includes information on programming the device. This is useful if you want to program the device yourself.

Device communication details (required for low-level programming): Before communicating with the device, **port B** of the FTDI USB controller must be setup for communication via the D2XX driver. Please refer to the FTDI D2XX Programmer's Guide on the FTDI web site (www.ftdichip.com) for general information on interfacing the FT2232H USB chip. CCD commands to the device are sent via USB as single **command bytes, immediately followed by the corresponding data bytes** in the **binary** (not ASCII) format. The required number of data bytes will depend on the command. The device follows the "command – response" pattern and will always send a reply to the host PC. For some commands the reply will be an acknowledgement **ACK** (hex: 0x06) for valid commands and data; or a non-acknowledgement **NACK** (hex: 0x15) for invalid commands (e.g. unknown command) or for invalid data (e.g. data out of range). For acquisition commands the reply will be a **sequence of bytes representing the returned pixel data** values. For other device query commands the reply will contain values consisting of multiple bytes (e.g. the serial number). **All data is sent and received most significant bit (MSB) first, followed by the least significant bits (LSBs).**

4.6.1. Configuration Commands

Set Integration Time Command

This command sets the integration time in microseconds (μs). The valid range is from 10 μs to 60 s.

For integration times from 10 μs to 3709 μs the sensor operates in shutter mode. For integration times equal to or above 3710 μs the sensor operates in non-shutter mode.

Important notes:

In single shot mode the integration time should be set to $\leq 500 \mu\text{s}$.

The integration time setting will be ignored in external synchronization trigger mode because the external trigger period will define the integration time in that mode.

Unit: microseconds (μs)

Valid range: 10 μs – 60 000 000 μs

Default: 5000 μs = 5 ms

Command byte (hex): 0xC1

Data: 32-bit unsigned integer (4 bytes), MSB first

Reply from device: ACK (0x06) or NACK (0x15)



Set Number of Frames (also Scans or Readouts) Per Acquisition Command

This command sets how many frames will be captured in one acquisition. This setting applies to onboard data storage mode only. The maximum possible number of frames per acquisition is limited by the internal RAM of the device to 4599 (or 4541 if the user has chosen to include the dummy pixels in the readouts).

Important note: This setting will be ignored in streaming mode because the number of frames is not limited in that mode and acquisition will continue until it is manually stopped.

Unit: N/A

Valid range: 1 – 4599 (4541 if dummy pixels are included in readouts)

Default: 1

Command byte (hex): 0xC2

Data: 32-bit unsigned integer (4 bytes), MSB first

Reply form device: ACK (0x06) or NACK (0x15)

Set CCD Operating Mode Command

This command sets the operating mode of the CCD. The five operating modes define the behavior of the device (external or internal synchronization, trigger types, etc.).

The available operating modes are:

- **0: Internally synchronized, continuously running, with software capture start**
- **1: Internally synchronized, continuously running, with hardware capture start**
- **2: Internally synchronized, continuously running, with hardware capture enable**
- **3: Single-shot, clean & ready with external hardware trigger**
- **4: Externally synchronized, continuously running, with software capture start**

Unit: N/A

Valid range: 0 – 4 (please note that the first mode is number 0)

Default: 0 (Internally synchronized, continuously running, with software capture start)

Command byte (hex): 0xC3

Data: 8-bit unsigned integer (1 byte), MSB first

Reply form device: ACK (0x06) or NACK (0x15)



Set Trig Out Before Integration Offset Command

This command sets the trig out offset prior to integration start in microseconds (μs). This offset can be used to indicate in advance that the integration will begin shortly but it is applicable **only when the sensor is in shutter mode (i.e. $T_{\text{int}} < 3710 \mu\text{s}$)** and applies **only to the following four operating modes**:

- Internally synchronized, continuously running, with software capture start
- Internally synchronized, continuously running, with hardware capture start
- Internally synchronized, continuously running, with hardware capture enable
- Single-shot, clean & ready with external hardware trigger

Important notes:

In the above operating modes when the sensor is in non-shutter mode this setting will be ignored as the integration begins at the start of a new frame and the offset is always $0 \mu\text{s}$.

In external synchronization mode this setting is also ignored as the trig out signal has a different meaning and indicates when integration has finished (not when it has started).

Unit: microseconds (μs)

Valid range: $0 \mu\text{s} - 1849 \mu\text{s}$

Default: $0 \mu\text{s}$ (= no offset)

Command byte (hex): $0xC4$

Data: 32-bit unsigned integer (4 bytes), MSB first

Reply from device: ACK ($0x06$) or NACK ($0x15$)

Set Hardware Dark Correction Command

This command turns the hardware dark correction of the device on or off. If this option is enabled (1) the optically black pixels at the beginning of the sensor will be used to compute the average dark level for each frame in real time in hardware. This level will be then subtracted from the current signal level for all active pixels of that frame.

Important note: This setting will be ignored if the dummy pixels are set to be included in the readouts.

Unit: N/A

Valid range: 0 or 1 (0 = disabled, 1 = enabled)

Default: 0 (= disabled)

Command byte (hex): $0xC5$

Data: 8-bit unsigned integer (1 byte), MSB first

Reply from device: ACK ($0x06$) or NACK ($0x15$)



Include Dummy Pixels in Readouts Command

This advanced command is normally not used. We recommend leaving this setting disabled. This advanced setting defines if the dummy pixels of the CCD sensor will be included in readouts. Because most of these pixels do not contain any useful information this setting should be normally left disabled. If disabled, only the active pixels of the CCD are include in readouts which is the default.

Important note: If this setting is enabled, the Hardware Dark Correction setting will be always disabled.

Unit: N/A

Valid range: 0 or 1 (0 = disabled, 1 = enabled)

Default: 0 (= disabled)

Command byte (hex): 0xC9

Data: 8-bit unsigned integer (1 byte), MSB first

Reply form device: ACK (0x06) or NACK (0x15)



4.6.2. Acquisition Commands

After having configured the device to the desired operating mode and parameters, one can initiate an acquisition. By using the commands described below.

Initiate Acquisition in Onboard Data Storage Mode Command (Acquisition Will Auto-Stop after Capturing the Preset Number of Frames)

This command initiates an acquisition for the preset number of frames (scans). Up to 4599 captured frames can be set to be stored in onboard RAM. After acquisition of the specified number of frames is complete, the device immediately starts sending all captured data to the PC. This data must be then fetched by the host PC. Before the acquired data has been fetched, the device cannot process further commands.

Command byte (hex): 0xC6

Data: N/A

Reply from device: When acquisition of the specified number of frames has finished, the device will return all pixel data values from all captured frames. Each frame consists of 3648 pixel data values (or 3694 pixel data values if the dummy pixels are included). Each data value is 16 bits (2 bytes), MSB first.

Initiate Acquisition in Data Streaming Mode and Stream Data Until Manually Stopped Command (Does Not Use the Preset Number of Frames)

This command initiates an acquisition in data streaming mode. In this mode the device will immediately stream any captured data to the host PC. There is no frame limit. The only limit is the storage device used (please also observe the maximum file size allowed by the underlying file system used on your storage device). In this advanced mode the configured number of frames (scans) per acquisition is completely ignored. Instead, the acquisition of triggered scans will continue until it is manually stopped by sending the **Stop Acquisition and Data Streaming** command (described below). After receiving the stop command, the device will capture one more frame and then stop acquisition. During streaming, the onboard RAM is used as a big FIFO frame buffer and prevents data overflow during capture.

During acquisition, acquired data will be continuously streamed to the PC and each scan must be fetched in time. The device features advanced buffering technology allowing the PC to fetch the data without buffer overflows. Nevertheless, the user must make sure that data is fetched as soon as possible and written to disk. Because in streaming mode the constant data rate is very high, it is not recommended to attempt to view the streaming data in real time. Instead, write the data to disk and view it later.

Programming logic tips: As described, during streaming one should periodically fetch captured frames. As soon as acquisition has been stopped by calling the *Stop Acquisition and Data Streaming* command, it is not sure if there are more scans to



arrive that have to be fetched. If there are frames left in the buffer after acquisition is stopped, they will be still streamed to the PC. Therefore, the incoming device buffer should be checked for pending data even after acquisition has been stopped; if there is such data, it should be fetched. If there is no data in the buffer for a longer time, the last streaming data has been already fetched and the acquisition is complete.

The FIFO RAM buffer is very large and should be able to buffer data without overflowing if the data is regularly fetched by the host PC. Nevertheless, if the buffer should overflow for some reason, this will be indicated by the red error LED on the device. In this case, streaming will be aborted. Please disconnect and reconnect the device from USB in order to reset it in case of this error.

Programming in data streaming mode is recommended for advanced users only. If you are using LabVIEW, please look at the included data streaming examples for more information.

Command byte (hex): 0xC7

Data: N/A

Reply from device: Acquired pixel data values will be immediately and continuously *streamed* to the host PC during acquisition. After acquisition has been stopped, if there is still data in the frame buffer, it will be also streamed to the PC. Each frame consists of 3648 pixel data values (or 3694 pixel data values if the dummy pixels are included). Each data value is 16 bits (2 bytes), MSB first.

Stop Acquisition and Data Streaming Command

This command stops the current acquisition and streaming in data streaming mode. In this advanced mode the configured number of scans per acquisition is completely ignored. Instead, the acquisition of triggered scans will continue until it is manually stopped by sending this command.

As soon as we have stopped acquisition by sending this command, we are not sure if there are more scans to arrive that have to be fetched. Therefore, we should continue to check for pending data in the incoming device buffer. If there is more data to be fetched, we can then fetch the scans. If there is no data in the buffer for a longer time, the last streaming data has been already fetched and the acquisition is complete.

Programming in data streaming mode is recommended for advanced users only. If you use LabVIEW, please look at the included data streaming examples for more information.

Command byte (hex): 0xC8

Data: N/A

Reply from device: The device will stream the last data left in the buffer.



4.6.3. Other Commands

Query Device Serial Number Command

This command queries the 64-bit (8-byte) serial number of the device.

Command byte (hex): 0xD1

Data: N/A

Reply form device: 64-bit unsigned integer (8 bytes), MSB first.

Query Device Hardware and Firmware Signature Command

This command queries the 64-bit (8-byte) hardware & firmware signature of the device.

Command byte (hex): 0xD2

Data: N/A

Reply form device: 64-bit unsigned integer (8 bytes), MSB first.



4.7. Time Needed to Acquire, Fetch & Display Frames (Measured in LabVIEW)

The time needed to initiate an acquisition from the host PC, capture all frames back-to-back, fetch those frames to the host PC and finally display them in a LabVIEW graph depends on multiple factors, including the hardware and speed of the host PC.

We have done some measurements with LabVIEW 8.6 and Windows XP on an Intel Core2Duo CPU notebook. The results may vary depending on the hardware and software running on the host PC. They are for information purposes only.

When acquiring **single frames** (one scan per acquisition) with $T_{\text{int}} = T_{\text{readout}} = 3.71$ ms, fetching these frames and **displaying** them in a LabVIEW graph we measured a total acquisition-to-acquisition delay of ~ 13 ms. This corresponds to an acquisition, fetch & display rate of ~ 77 Hz.

When acquiring the **maximum number of 4599 frames** that can be stored at once in onboard RAM (4599 scans per acquisition) with $T_{\text{int}} = T_{\text{readout}} = 3.71$ ms, fetching these frames, **averaging and displaying** them in a LabVIEW graph we measured a total acquisition-to-acquisition delay of ~ 26200 ms. This corresponds to ~ 5.7 ms for each frame.

Again, the values above are for information purposes only and will depend on the configuration of the host PC.

5. Connecting the CCD & Installing the USB Drivers



Please carefully read the following instructions, **BEFORE** connecting the device to the computer.

The CCD device has to be connected to a spare **USB 2.0 port** on your computer using an appropriate USB 2.0 cable. The cable must have a type B plug on the CCD side. Most host computers require a type A plug on the host side. Depending on your operating system, the driver installation will vary as described below.

5.1. Microsoft Windows 7 / Vista / XP

Microsoft Windows 7 / Vista / XP operating systems will indicate that new hardware has been found and will either install the driver without any user intervention or ask the user to confirm that the OS should search for the driver in the Windows Update database and will then install it automatically.

Microsoft Windows 7 / Vista / XP already have the required D2XX FTDI drivers in their database and are able to install them automatically. In most cases installation is extremely easy and will complete within seconds.

On device plug-in a message will pop up in the task bar indicating that a new ALPHALAS CCD-S3600-D(-UV) device has been found. The driver will be either installed without any user intervention (this is typical for Windows 7) or a wizard will indicate that new hardware has been found and ask if the OS should connect to Windows Update to search for the appropriate driver (this is typical for Windows Vista and Windows XP). The user should confirm and let the OS download and install the driver automatically.

Please note that the found new hardware wizard may pop up multiple times, because modern FTDI devices have multiple ports and use multiple drivers. Confirm the installation prompts until all drivers have been installed. The OS may need some time to find the drivers, download and install them. Please be patient and do not unplug the device until the drivers have been installed completely.

If the drivers have been installed correctly, two USB devices called **USB Serial Converter A** and **USB Serial Converter B** should have appeared in the Windows Device Manager under Universal Serial Bus Controllers. These devices represent both ports (A and B) of the dual-port FT2232H chip. In the advanced properties of these devices the "Load VCP" option should remain *unchecked*, which means that the driver will use the faster D2XX mode instead of the slower virtual com port (VCP) mode of the combined drivers.

For further information please refer to <http://www.ftdichip.com/FTDrivers.htm>.



5.2. Linux, Mac OS X, etc.

The CCD-S3600-D(-UV) uses the **FT2232H chip** from FTDI. The recommended USB drivers for this chip are the direct **D2XX** drivers, *not* the VCP (virtual COM port) drivers. The D2XX drivers are faster and the recommended choice for this high-speed chip. They are accessed through a special API. The LabVIEW applications included with the CCD device use these D2XX drivers.

As described previously, the latest Microsoft Windows OS should be able to install the appropriate drivers automatically. This is the easiest and recommended way to install the drivers in Windows OS. If you are using a different operating system like Linux or Mac OS or want to install or update your driver manually, please visit the FTDI website. At <http://www.ftdichip.com/Drivers/D2XX.htm> you can find the appropriate drivers for the FT2232H chip and for your specific OS. You should use the D2XX drivers for fastest performance and compatibility with the examples. Please read the driver installation instructions for your OS. On the FTDI website you can also find detailed troubleshooting instructions. Please note that ALPHALAS is not able to provide support for all operating systems supported by drivers.

5.2.1. Linux

Please note that on many modern **Linux** distributions (e.g. Ubuntu, openSUSE, etc.) FTDI drivers are already included with the kernel and will be loaded automatically as soon as the device is plugged in. However, the drivers that are loaded by default are **not the fast D2XX** drivers but the slower virtual com port (VCP) drivers which present the device to the OS as an emulated com port. The VCP drivers are not compatible with the D2XX API used in the examples. Therefore you should manually **install the fast D2XX Linux drivers** from <http://www.ftdichip.com/Drivers/D2XX.htm>. For installation details please refer to the Linux ReadMe files at that webpage.

Before you can use the D2XX drivers you must always **unload** the VCP drivers that have been automatically loaded by the kernel. This has to be done every time the device is plugged in. You can check if the VCP drivers have been loaded by entering **dmesg | grep FTDI**. If there are messages containing *ftdi_sio*, then the VCP drivers have been loaded and need to be unloaded first as root user or by running **sudo: sudo rmmod ftdi_sio** and **sudo rmmod usbserial**.

Another important thing is that the FTDI library makes use of libusb. In order to get access to a USB device you have to **run all programs that access the USB device as a root user** or by using **sudo**. For LabVIEW this means starting it like this:
sudo ./labview

Instead of using sudo as described above, you may also change the permissions by a udev rule like described here:

http://code.google.com/p/picusb/wiki/libusb_and_udev

The device's VID is 0x0403 and the PID is 0x6010.



5.2.2. Mac OS X

For **Mac OS X** installation notes please refer to the Mac OS X ReadMe files at <http://www.ftdichip.com/Drivers/D2XX.htm>. Make sure that you install the drivers compatible with your Mac OS X version.

If you are **only using LabVIEW for Mac** to access the CCD camera you may skip the installation for the USB drivers because LabVIEW for Mac accesses the device through a Mac OS X framework instead of using the driver libraries directly. Please refer to chapter 6.1.3 for detailed information.

5.2.3. Other OS

For **other operating systems** or **manual driver installation** instructions please refer to <http://www.ftdichip.com/Drivers/D2XX.htm>.

5.2.4. libftdi – An Alternative to D2XX

In addition to the closed source FTDI D2XX drivers & API, an **open source** alternative API called **libftdi** also exists. Libftdi works with Linux, Windows, MacOS X and BSD variants because it is based on the libusb driver. The user should be able to use this API, however ALPHALAS has not tested it and cannot provide support. The libftdi API is different from the D2XX API. For further details please refer to <http://www.intra2net.com/en/developer/libftdi/>.



6. LabVIEW Drivers & GUI Applications



Please carefully read the following instructions, **BEFORE** installing the LabVIEW drivers.

6.1. Installing the LabVIEW Drivers

6.1.1. Instructions for All Operating Systems

The LabVIEW drivers require the FTDI D2XX USB drivers to be installed first as described in the previous chapter. The only exception is on Mac OS X where the device is accessed through an extra framework, because LabVIEW versions prior to 2011 cannot access the dynamic libraries (*.dylib) of the D2XX driver directly.

In order to support older as well as newer LabVIEW versions, the driver has been created with LabVIEW 8.6 but it is also compatible with the latest versions of LabVIEW (e.g. LabVIEW 2011). The driver VIs will be automatically recompiled by the newer LabVIEW versions in the background when used for the first time and may prompt the user to save them for the newer LabVIEW version.

The LabVIEW drivers are located in the "**ALPHALAS CCD S Series**" subfolder of the "**LabVIEW Drivers and Applications**" folder provided to the customer via e-mail, on a CD-ROM or in a similar way. In order to install the drivers, simply copy the complete "**ALPHALAS CCD S Series**" folder including *all* of its contents into your LabVIEW "**instr.lib**" folder.

For your information: The LabVIEW "instr.lib" folder contains all instrument driver folders and is located in your main LabVIEW directory. Example: If you have installed LabVIEW into its **default** installation location, for LabVIEW 8.6 (English version) on Windows XP 32-bit your "instr.lib" folder would be the following:

"C:\Program Files\National Instruments\LabVIEW 8.6\instr.lib"

By default the LabVIEW driver is ready to be used with **Microsoft Windows**. For additional information on using the driver in LabVIEW for **Linux** please refer to chapter 6.1.2. For additional information on using the driver in LabVIEW for **Mac OS X** please refer to chapter 6.1.3.

6.1.2. Special Instructions for LabVIEW for Linux

If you are using LabVIEW for Linux first make sure that the FTDI D2XX Linux USB drivers have been installed as described in chapter 5.2.1. Also make sure that ftdi_sio and usbserial have been removed from the active modules via rmmmod as described in that chapter.



Make sure that you have copied the LabVIEW driver to your instr.lib folder as described in chapter 6.1.1. While the LabVIEW for Windows driver uses FTDI's *d2xx.dll* for Windows, the LabVIEW for Linux driver uses **libftd2xx.so** instead. For this reason you have to replace the folder **FTDI D2XX Functions** which contains the Windows files by default and is located in

Your LabVIEW Folder/instr.lib /ALPHALAS CCD S Series/Private

with the corresponding folder containing the Linux files by doing the following:

1. Shut down LabVIEW for Linux.
2. Rename the existing **FTDI D2XX Functions** folder to **Windows FTDI D2XX Functions**
3. Rename the **Linux FTDI D2XX Functions** folder to **FTDI D2XX Functions**

Now the FTDI D2XX Functions folder contains the required Linux files and the LabVIEW drivers are ready for use with Linux.

Another important thing is that the FTDI library makes use of libusb. In order to get access to a USB device you have to **run all programs that access the USB device as a root user** or by using **sudo**. For LabVIEW this means starting it like this:
sudo ./labview

Instead of using sudo as described above, you may also change the permissions by a udev rule like described here:

http://code.google.com/p/picusb/wiki/libusb_and_udev

The device's VID is 0x0403 and the PID is 0x6010.

6.1.3. Special Instructions for LabVIEW for Mac OS

Make sure that you have copied the LabVIEW drivers to your instr.lib folder as described in chapter 6.1.1.

It is important to note that LabVIEW for Mac versions prior to 2011 are not able to use the dynamic shared libraries (*.dylib) included in the FTDI D2XX Mac OS X drivers directly. Therefore, a special framework had to be created. After having installed the LabVIEW driver as described in chapter 6.1.1 you can find this framework in **Your LabVIEW Folder/instr.lib/ALPHALAS CCD S Series/Private/Framework for Mac OS X for FTDI D2XX**

directory. Please also refer to the README file in that folder. In order to install the driver framework, please do the following:

1. First copy the libftd2xx.framework.zip contained in this folder to your Mac desktop (do NOT unzip it in Microsoft Windows because important properties of the files will get lost!).
2. Unzip the libftd2xx.framework.zip file on your Mac by double clicking it. It should be now extracted into a libftd2xx.framework folder.
3. Copy this complete libftd2xx.framework folder to the existing /Library/Frameworks folder on your Mac.

4. You should now have a /Library/Frameworks/libftd2xx.framework folder. While the LabVIEW for Windows driver uses FTDI's *d2xx.dll* for Windows, the LabVIEW for Mac OS X driver uses the **libftd2xx.framework** instead. For this reason you have to replace the folder **FTDI D2XX Functions** which contains the Windows files by default and is located in **Your LabVIEW Folder/instr.lib /ALPHALAS CCD S Series/Private** with the corresponding folder containing the Mac files by doing the following:

1. Shut down LabVIEW for Mac.
2. Rename the existing **FTDI D2XX Functions** folder to **Windows FTDI D2XX Functions**
3. Rename the **Mac FTDI D2XX Functions** folder to **FTDI D2XX Functions**

Now the FTDI D2XX Functions folder contains the required Mac files and the LabVIEW drivers are ready for use with your Mac.

6.2. Using the LabVIEW Drivers

After having installed the LabVIEW drivers as described in chapter 6.1, please restart LabVIEW.

If the installation is successful you should be able to access the "**ALPHALAS CCD S Series**" instrument driver VIs through the palette menu:

1. Go to the block diagram of any VI and right-click to open the "**Functions Palette**".
2. In the "Functions Palette" you should be able to locate the driver VIs under "**Instrument I/O >> Instrument Drivers >> ALPHALAS CCD S Series**".

The main palette icon of ALPHALAS CCD S Series looks like this .

The palette contents are shown in Figure 6-1.




Figure 6-1: The LabVIEW Driver in the Functions Palette

The driver structure is shown in the “VI Tree VI” in Figure 6-2:




Figure 6-2: The LabVIEW Driver Structure Shown in the VI Tree VI

- The driver contains the common “Initialize VI” and “Close VI”.
- The CCD device can be configured using the “Configure Acquisition VI”.
- Making an acquisition of the number of scans set by the user and finally fetching all data can be done by using the high-level “Acquire Preset Number of Scans and Fetch Data VI”. The low-level data VIs can be used for finer control of the device in *preset number of scans* mode or in the more advanced *data streaming* mode.
- The utility VIs can be used to query the device properties, the device hardware and firmware, the device serial number and the driver revision.

All driver VIs are well documented. Please use the LabVIEW Context Help to access the documentation.



6.3. LabVIEW Examples & GUI Application VIs

Fully-functional LabVIEW GUI application VIs are included with the device. All drivers and VIs are modern project-style, designed for plug&play operation. The VIs include well-commented block diagrams, front panels and context help and are built according to the National Instruments LabVIEW development guidelines.

LabVIEW applications & examples include:

- Single Acquisition VI
- Acquisition Loop VI
- Acquisition Loop with Runtime-Changeable Parameters VI
- 3D-Realtime-Graph (Active X Version) VI
- 3D-Realtime-Graph (Native Version) VI
- Data Streaming to File VI
- Viewer for Streamed Data from File VI
- Gaussian Fit Loop VI
- Acquisition Loop with Save and Load and Full-Width Half-Maximum Calculation VI
- Acquisition Loop with Multiple CCD Cameras VI
- Device Information VI
- Speed Test VI

All application VIs and driver VIs contain documentation and comments.

All driver VIs and applications are contained in a single LabVIEW project.

Please open the "**ALPHALAS CCD S Series.lvproj**" project file in your "**instr.lib\ALPHALAS CCD S Series**" folder in your main LabVIEW directory. The application & example VIs, are in the folder "**Examples**". See Figure 6-3.




Figure 6-3: The LabVIEW Project Containing the Example VIs

Before running any example VIs you need to have the CCD device connected to the computer and the USB drivers as well as the LabVIEW drivers installed, as described in the previous sections of this manual.



Make sure that you have set all parameters to valid values before running the example applications. To read the documentation of the example VIs, please use the LabVIEW Context Help and see the comments on the front panels and block diagrams.

In the following figures screenshots of some of the example VIs are shown. For further information please refer to the front panel comments as well as the block diagrams of the VIs.




Figure 6-4: Acquisition Loop with Runtime Changeable Parameters VI




Figure 6-5: Data Streaming to File VI




Figure 6-6: View Streamed Data from File VI




Figure 6-7: Acquisition Loop with 3D Graph VI

Please note that the Active X version of this example can be run on Windows OS only, as other OS do not support Active X.




Figure 6-8: Acquisition Loop with Save and Load and FWHM Calculation VI



7. C++ Examples

The included C++ examples demonstrate how to interface and use the CCD-S3600-D-(UV) device from C++. The well-commented cross-platform console application code will initialize & configure the device with the user-specified parameters; then it will acquire and fetch the data and will finally print the values on the screen and write them into a comma-separated text file (CSV) as well as a binary file (big-endian).

All examples are located in the "**C++ Examples**" folder provided to the customer via e-mail, on a CD-ROM or in a similar way. The subfolders include:

- A **Visual C++** project for **Microsoft Windows**. This project is also compatible with the free Express edition of Visual C++. The project also contains the built executable (.exe) example for Windows.
- A **GCC C++** project for **Linux, Mac OS X** and other OS.

The source code is actually the same for Visual C++ and for GCC C++ and can be compiled under Windows, Linux, Mac OS X, etc. This is a good example that cross-platform development and access to the CCD camera is possible.

7.1. Microsoft Visual C++ for Windows




Figure 7-1: The Included Microsoft Visual C++ Project



These instructions have been written for Microsoft Visual C++ 2010 Express but should apply in a similar way to other versions of the software.

The VC++ project requires **ftd2xx.dll** which should have been already installed with the FTDI D2XX driver into the Windows system folder. This project also requires **ftd2xx.lib** and **ftd2xx.h** which are included with the FTDI D2XX driver available on the FTDI website. Both files must be made available in the same folder as the source code CCD-S3600-D_D2XX_Example.cpp file.

ftd2xx.lib must be also added to the Visual C++ project through Project > CCD-S3600-D_D2XX_Example Properties... > Configuration Properties > Linker > Input > **Additional Dependencies**.

Make sure that **ftd2xx.lib** is added to that additional dependencies **list of .lib files separated by a semicolon and for all configurations** (Debug and Release).

For further information please refer to the files in the project directory.

7.2. GCC C++ for Linux, Mac OS X, etc.

Make sure that the FTDI D2XX Driver for Linux / Mac OS X has been installed from <http://www.ftdichip.com/Drivers/D2XX.htm>.

Make sure that the GNU Compiler Collection GCC C++ compiler is installed correctly. In order to install GCC for Mac OS X you should install Apple's Xcode development environment.

Make sure that the **ftd2xx.h** and **WinTypes.h** files from the Linux / Mac OS X driver are accessible from the main C++ program (e.g. place them in the same folder).

To build the example, use the following GCC statement (assuming you have the D2XX library installed in the /usr/local/lib directory):

```
g++ -o CCD-S3600-D_D2XX_Example CCD-S3600-D_D2XX_Example.cpp -L.  
-lftd2xx -Wl,-rpath /usr/local/lib
```

Notes for Linux:

As described in chapter 5.2.1, because the example uses the D2XX driver you need to first unload any VCP drivers loaded by the kernel by running **sudo rmmod ftdi_sio** and **sudo rmmod usbserial**.

Another important thing is that the FTDI library makes use of libusb. In order to get access to a USB device you have to **run all programs that access the USB device**



as a root user using sudo. For the compiled example code this means starting it like this: **sudo ./CCD-S3600-D_D2XX_Example.**

Instead of using sudo as described above, you may also change the permissions by a udev rule like described here:

http://code.google.com/p/picusb/wiki/libusb_and_udev

The device's VID is 0x0403 and the PID is 0x6010.

For further information please refer to the files in the source code directory.



8. Maintenance

The device is **not** water resistant. Do not expose the device to spray, liquids or solvents.

Also when disconnected, the CCD device must be protected from electrostatic charges. Keep the device and the cables in a clean, dry and dust-free place.



FOR CLEANING THE DETECTOR WINDOW PLEASE USE ISOPROPYL ALCOHOL. AVOID SCRATCHING THE WINDOW. ALWAYS DISCONNECT THE DEVICE BEFORE CLEANING.

In case of malfunction, please contact ALPHALAS. Do not try to open or repair the device. Doing so will void any warranty. There are no parts in the device that can be repaired by the customer himself.



9. Troubleshooting

The device is not recognized by the computer

- Make sure that the FTDI D2XX driver is installed correctly and the FTDI USB device shows up correctly in the device manager of your operating system. The latest Microsoft Windows operating systems should be able to install the driver automatically.
For detailed information, also refer to www.ftdichip.com and the driver installation instructions listed there.
- Make sure that you have administrator privileges on the computer.
- Restart the computer and see if the problem persists.
- Make sure that your computer (especially if using a notebook) can supply 500 mA to the USB port as required by the USB standard.
- Try to attach the device to a different USB port.
- Try to install the device on a different computer to make sure that there is no installation problem or conflict related to a specific computer.

The device does not return from acquisition, it appears frozen

- If using CCD operating modes that require the external trigger input signal, make sure that this signal is applied correctly and actually triggers the device.
- Make sure that the acquisition has actually completed; especially if you have set a long integration time or multiple scans per acquisition. Also make sure that the external trigger has triggered the requested number of scans. If using data streaming mode, make sure that the acquisition has been stopped and the last frames have been triggered.
- To reset the device and abort the acquisition in progress, disconnect and reconnect the device.

Acquisition starts but after some time it is interrupted

- If you are acquiring data for a longer time make sure that the computer does **not** enter any standby or sleep modes. If this happens, the USB ports will be disabled and the acquisition will be interrupted. This is expected behavior.